

Product data sheet

Specifications



FULL-VOLTAGE NON-REVERSING IEC STARTER CIRCUIT BREAKER 30A TYPE 12

LE1D129E72OG70

⚠ **Discontinued on:** Nov 11, 2020

⚠ **End-of-service on:** Dec 31, 2020

⚠ **Discontinued**

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Product or Component Type	Full voltage starter
Range of Product	Instakit
Starter Type	Non reversing
Disconnect Type	PowerPact motor circuit protector

Complementary

Control Circuit Voltage	120 V AC 50/60 Hz
Current Rating	12 A
Horsepower Rating	0.5 hp 120 V AC, 1 phase 2 hp 240 V AC, 1 phase 3 hp 208 V AC, 3 phase 3 hp 230 V AC, 3 phase 7.5 hp 460 V AC, 3 phase 10 hp 575 V AC, 3 phase
Maximum Voltage Rating	600 V AC
Auxiliary Contacts	1 NO + 1 NC
Protection Type	Motor circuit protector 30 A
Location of connection	Line

Environment

Product Certifications	UL CSA IEC
Enclosure Type	NEMA 12 steel

Ordering and shipping details

Category	US10I1122313
Discount Schedule	0I11
GTIN	00785901212744
Returnability	No

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
EU RoHS Directive	Compliant
California proposition 65	WARNING: This product can expose you to chemicals including: Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer. For more information go to www.P65Warnings.ca.gov
PVC free	Yes

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.