

Product data sheet

Specifications



FULL-VOLTAGE NON-REVERSING IEC STARTER CIRCUIT BREAKER 30A TYPE 1

LE1D099E62OG70

⚠ Discontinued on: Nov 6, 2025

⚠ End-of-service on: Dec 31, 2025

⚠ Discontinued

Main

Product or component type	Full voltage starter
Range of product	Instakits
Starter Type	Non reversing
Disconnect Type	PowerPact motor circuit protector

Complementary

Control Circuit Voltage	120 V AC 50/60 Hz
Current Rating	9 A
Horsepower Rating	0.3 hp 120 V AC, 1 phase 1 hp 240 V AC, 1 phase 2 hp 208 V AC, 3 phases 2 hp 230 V AC, 3 phases 5 hp 460 V AC, 3 phases 7.5 hp 575 V AC, 3 phases
Maximum Voltage Rating	600 V AC
Auxiliary Contacts	1 NO + 1 NC
Protection type	Motor circuit protector 30 A
Location of connection	Line

Environment

Product certifications	UL CSA IEC
Enclosure Type	NEMA 1 steel

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Compliant
PVC free	Yes

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
Circularity Profile	No need of specific recycling operations
WEEE Label	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins