

Product datasheet

Specifications



blown fuse indicator 1NO 1NC - for Fupact INF

49634

! Discontinued

Main

Range of product	INF100...160
Range	FuPact
Device short name	blown fuse indicator
Product or component type	Blown Fuse Indicator
Device application	Display
Range compatibility	FuPact Fupact INF fuse-switch disconnecter
Poles description	3P 4P
Signal contacts composition	1 NC 1 NO

Complementary

[I _{th}] conventional free air thermal current	16 A
[I _e] rated operational current	AC-15: 6 A at 24 V AC 50/60 Hz DC-12: 2 A at 48 V DC DC-12: 6 A at 24 V DC AC-15: 2 A at 660/690 V AC 50/60 Hz AC-15: 3 A at 440 V AC 50/60 Hz AC-15: 4 A at 380/415 V AC 50/60 Hz AC-15: 6 A at 110 V AC 50/60 Hz AC-15: 6 A at 220/240 V AC 50/60 Hz AC-15: 6 A at 250 V AC 50/60 Hz AC-15: 6 A at 48 V AC 50/60 Hz DC-12: 0.1 A at 380/415 V DC DC-12: 0.1 A at 440 V DC DC-12: 0.4 A at 220/240 V DC DC-12: 0.4 A at 250 V DC DC-12: 1.1 A at 110 V DC
Minimum load	10 mA at 24 V

Contractual warranty

Warranty (in months)	18
----------------------	----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer



Lifetime extension

Repair

No

Use Again



Repack and remanufacture

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins