

Control and signaling units

Harmony XB5, plastic

Diameter 22 mm selector switches with standard handle



XB5AD33



XB5AD33C0



ZB5AD2



ZB5AD204

Selector switches with standard handle ⁽¹⁾

Screw clamp terminal connections (Schneider Electric anti-loosening system)

Shape of head	Type of operator	Type of contact		Positions		Reference		Weight kg/lb
		NO	NC	Number	Type			
						For black bezel	For gray bezel	

Complete units ⁽²⁾

	Standard handle, black	1	–	2-position 90°	Stay put	↙	XB5AD21 ⁽³⁾ (ZB5AZ101 + ZB5AD2)	XB5AD21C0 (ZB5AZ101 + ZB5AD2C0)	0.043/0.095
		1	–		Spring return from right to left	↘	XB5AD41 (ZB5AZ101 + ZB5AD4)	XB5AD41C0 (ZB5AZ101 + ZB5AD4C0)	0.046/0.101
		1	1		Stay put	↙	XB5AD25 (ZB5AZ105 + ZB5AD2)	XB5AD25C0 (ZB5AZ105 + ZB5AD2C0)	0.043/0.095
		2	–	3-position ± 45°	Stay put	↙	XB5AD33 (ZB5AZ103 + ZB5AD3)	XB5AD33C0 (ZB5AZ103 + ZB5AD3C0)	0.043/0.095
					Spring return to center	↕	XB5AD53 (ZB5AZ103 + ZB5AD5)	XB5AD53C0 (ZB5AZ103 + ZB5AD5C0)	0.043/0.095

Heads only ⁽²⁾

	Standard handle, black	2-position 90°	Stay put	↙	ZB5AD2	ZB5AD2C0	0.017/0.037
			Spring return from right to left	↘	ZB5AD4	ZB5AD4C0	0.020/0.044
		3-position ± 45°	Stay put	↙	ZB5AD3	ZB5AD3C0	0.017/0.037
			Spring return to center	↕	ZB5AD5	ZB5AD5C0	0.017/0.037
			Spring return from left to center	↖	ZB5AD7	ZB5AD7C0	0.017/0.037
			Spring return from right to center	↗	ZB5AD8	ZB5AD8C0	0.017/0.037

Heads only with other colored handles ⁽²⁾

	Standard handle, white	Add suffix 01 to the reference, for example: ZB5AD201		ZB5AD201C0
	Standard handle, green	Add suffix 03 to the reference, for example: ZB5AD203		ZB5AD203C0
	Standard handle, red	Add suffix 04 to the reference, for example: ZB5AD204		ZB5AD204C0
	Standard handle, yellow	Add suffix 05 to the reference, for example: ZB5AD205		ZB5AD205C0
	Standard handle, blue	Add suffix 06 to the reference, for example: ZB5AD206		ZB5AD206C0

⁽¹⁾ For recommended maximum number of contacts and sequence of contacts constituting the body (fixing collar and contact) associated with the head, see [page 26](#) and [27](#).⁽²⁾ To add customized markings on these references using the web customization tool, see [page 5](#).⁽³⁾ To order products with 1NO and 1NC contact, replace the last digit of the commercial reference with a 5, example: XB5AA21 becomes XB5AA25.