

# Product data sheet

Specifications



## coil LX1-LC - 48 V AC 50/60Hz

LX1LC0489

⚠ Discontinued on: Jul 12, 2021

⚠ Discontinued

### Main

Range	TeSys
Device short name	LX1
Product or Component Type	Coil
[Uc] control circuit voltage	48 V AC 50/60 Hz
Power consumption in VA	12...18 VA AC 0.3 60 Hz sealed 170...230 VA AC 0.55 60 Hz inrush
Value of inductance	0.107 mH closed circuit
Average resistance	13.349 Ohm +/- 10 %

### Complementary

Range compatibility	TeSys LX1 contactor
Net Weight	0.26 lb(US) (0.12 kg)

### Ordering and shipping details

Category	22384-STARTERS,INTEGRAL,ACCESS
Discount Schedule	I11
GTIN	3389110246322
Returnability	No
Country of origin	FR

### Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.6 in (6.7 cm)
Package 1 Width	1.8 in (4.5 cm)
Package 1 Length	3.1 in (8 cm)
Package weight(Lbs)	4.9 oz (140 g)

### Contractual warranty

Warranty (in months)	18
----------------------	----

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)



### Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

## Use Better



### Materials and Substances

[EU RoHS Directive](#)

Pro-active compliance (Product out of EU RoHS legal scope)

California proposition 65

WARNING: This product can expose you to chemicals including: Antimony oxide & Antimony trioxide, which is known to the State of California to cause cancer. For more information go to [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov)

## Use Longer



### Lifetime extension

Repair

No