

Product datasheet

Specifications



RFI filter 300A/400V - ATV68

VW3A68402

⚠ End-of-service on: Nov 24, 2021 AD

⚠ Discontinued

Main

Range of product	Altivar
Product or component type	EMC input filter
Range compatibility	Altivar 68
Product compatibility	Variable speed drive ATV68 motor: 110 kW, 400...500 V Variable speed drive ATV68 motor: 132 kW, 400...500 V Variable speed drive ATV68 motor: 160 kW, 400...500 V
Product specific application	Radio interference input filter
[In] rated current	300 A
Thermal losses	40 W
Network number of phases	Three phase

Complementary

maximum earth leakage current	100 mA at 400 V 50 Hz TN 100 mA at 400 V 50 Hz TT
power supply voltage	400...500 V
Tolerance	15 %
Width	204 mm
Height	295 mm
Depth	89 mm

Contractual warranty

Warranty (in months)	18
----------------------	----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer



Lifetime extension

Repair

No