

# Product datasheet

Specifications



## TeSys Integral - undervoltage trip - 110 V AC 50 Hz - without time delay

LA1LC072F

⚠ Discontinued on: 27 Aug 2020

⚠ Discontinued

### Main

Range	TeSys
Device short name	LA1LC
Product or component type	Undervoltage trip
Product compatibility	LD5 LD4
Range compatibility	TeSys TeSys Integral contactor breaker

### Complementary

[Uc] control circuit voltage	110 V AC 50 Hz 110...120 V AC 60 Hz
Time delay	Without time delay
Voltage release type	Undervoltage release Instantaneous
Control circuit voltage limits	0.8...1.1 Uc
Threshold tripping voltage	0.35...0.7 Uc
Inrush power in VA	8 VA AC
Hold-in power consumption in VA	4 VA AC
Quantity per set	Set of 10
Net weight	0.15 kg

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.4 cm
Package 1 Width	6.3 cm
Package 1 Length	11.5 cm
Package 1 Weight	134 g

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

#### Materials and Packaging

EU RoHS Directive

[Compliant](#)

### Use Longer

#### Lifetime extension

Repair

No

### Use Again

#### Repack and remanufacture

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins