

Product datasheet

Specifications



EMC radio interference input filter ≤ 42 A - 30 W - 3-phase supply

VW3M4101

⚠ Discontinued on: 4 Aug 2021

⚠ End-of-service on: 18 Oct 2024

⚠ Discontinued

EAN Code: 3389119210737

Main

Range of product	Lexium
Product or component type	EMC input filter
Range compatibility	Lexium 15
Product compatibility	LXM 15HC11N4X
Product specific application	Radio interference input filter
[In] rated current	42 A
Thermal losses	30 W
Network number of phases	Three phase

Complementary

Electrical connection	Terminal 25 mm² AWG 2
power supply voltage	380...500 V 200...240 V
Tolerance	10 %
Net weight	0.6 kg

Environment

IP degree of protection	IP20
Standards	EN/IEC 61800-3 UL 1283

Contractual warranty

Warranty (in months)	18
----------------------	----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer

Lifetime extension	
Repair	No