

PL Series Three Phase Main Lug & Main Breaker Load Centers

3-phase, 3-wire, 240 Volt AC or 3-phase, 4-wire, 120/240 or 120/208 Volts AC

Main Breaker/Convertible Load Centers 30-70 Circuits / 100-225 Amperes

Copper Bus^{⑧⑩}
60/75°C Rated 22,000A IR^①

Branch Circuits			Indoor Enclosure – NEMA Type 1		Outdoor Enclosure – NEMA Type 3R	
Amp Rating	No. of Spaces	No. of Circuits	Catalog Number	Enclosure Height (inches) ^③	Catalog Number	Enclosure Height (inches) ^④
100	12	24	P1224B3100CU ^② NEW!	24	—	—
100	30	42	P3042B3100CU ^②	30	—	—
125	30	30	P3030B3125CU NEW!	39	—	—
150	24	42	P2442B3150CU	36	—	—
150	42	42	P4242B3150CU NEW!	42	—	—
200	30	54	P3054B3200CU	39	PW3054B3200CU	38
200	42	60	P4260B3200CU	42	PW4260B3200CU	42
225	42	60	P4260B3225CU NEW!	42	—	—
225	42	60	P4260B3225TCU ^⑥	49	—	—
225	54	70	P5470B3225CU	49	—	—

Three phase factory installed 22ka IR main breaker offers 22/10kA series combination rating when using 10kA type QP, QT, QPF, QE, QN, and QAF/QAFC branch breakers.

Main Lug/Convertible Load Centers^⑤ 12-70 Circuits / 125-225 Amperes

Copper Bus^{⑧⑩}
60/75° Rated 100,000A IR^⑨

Branch Circuits			Indoor Enclosure – NEMA Type 1		Outdoor Enclosure – NEMA Type 3R	
Amp Rating	No. of Spaces	No. of Circuits	Catalog Number	Enclosure Height (inches) ^③	Catalog Number	Enclosure Height (inches) ^④
125	12	24	P1224L3125CU ^⑦	21	PW1224L3125CU ^⑦	21
200	24	42	P2442L3200CU	36	PW2442L3200CU	35
200	30	54	P3054L3200CU	39	PW3054L3200CU	38
225	42	60	P4260L3225CU	42	PW4260L3225CU ^⑩	42
225	54	70	P5470L3225CU	49	—	—

① May be installed on higher rated systems when protected by a circuit breaker with a higher AIR rating.

② Back fed main breaker.

③ Indoor enclosures are 14 1/4" wide by 3 7/8" deep.

④ Outdoor enclosures are 14 1/2" wide by 4 1/4" deep.

⑤ Suitable for use as service entrance equipment when not more than six main disconnecting means are provided. See article 230.71 of the NEC.

⑥ Includes factory installed feed through lugs and is also non-convertible.

⑦ Non-convertible to main breaker.

⑧ All load centers are provided with tin plated copper bus bars.

⑨ Rated 100,000A IR in series with breakers listed on wiring diagram.

⑩ All load centers are provided with tin-plated copper bus bars.