

# Product data sheet

Specifications



## universal protection relay, PowerLogic P3U 3CT 1Io 14DI 11DO 48-230V DI110 RS485 RL

REL53152

**Product availability: Non-Stock - Not normally stocked in distribution facility**

### Main

|                                |                                                                                     |
|--------------------------------|-------------------------------------------------------------------------------------|
| Range of Product               | PowerLogic P3                                                                       |
| Product or Component Type      | Protection relay                                                                    |
| Relay application              | Universal                                                                           |
| product reference              | P3U30-6AAA2BGAB                                                                     |
| Mounting case size             | 30TE                                                                                |
| Device mounting                | Flush                                                                               |
| Mounting Mode                  | Flush mounting                                                                      |
| power supply                   | 24...48 V AC/DC                                                                     |
| measuring inputs               | 3 1/5 A CT phase current<br>1 1/5 A CT residual current<br>4 100 V/110 V VT voltage |
| Number of sensors              | 0 temperature sensor(s)<br>0 arc sensor(s)                                          |
| number of Digital Inputs (DI)  | 14                                                                                  |
| number of analogue inputs      | 0                                                                                   |
| number of Digital Outputs (DO) | 11 DO<br>1 watchdog                                                                 |
| number of analogue outputs     | 0                                                                                   |
| communication ports            | Front USB port 1<br>Rear RS485 1                                                    |
| communication protocols        | IEC 60870-5-101<br>IEC 60870-5-103<br>DNP3<br>Modbus RTU<br>DeviceNet<br>SPABus     |
| Cybersecurity                  | Password protection<br>Port hardening                                               |

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

|                      |                                               |
|----------------------|-----------------------------------------------|
| protection functions | Phase overcurrent 50/51                       |
|                      | Directional phase overcurrent 67              |
|                      | Earth fault overcurrent 50N/51N               |
|                      | Directional earth fault 67N                   |
|                      | Transient earth fault 67NI                    |
|                      | Capacitor bank unbalance 51C                  |
|                      | Broken conductor 46 I2/I1 8                   |
|                      | Cold load pick-up 67NI                        |
|                      | Cold load pick-up 68H2                        |
|                      | H2 detection 68H2                             |
|                      | H5 detection 68H5                             |
|                      | Breaker failure 50BF                          |
|                      | Switch ON to fault (SOTF) 68H5                |
|                      | Directional active underpower 37P             |
|                      | Fault locator 21FL                            |
|                      | Recloser 79                                   |
|                      | Phase undercurrent 37                         |
|                      | Excessive starting time, locked rotor 48/51LR |
|                      | Motor restart inhibition 66                   |
|                      | Capacitor overvoltage 59C                     |
|                      | Negative sequence overcurrent 46              |
|                      | Switch ON to fault (SOTF) 50/51               |
|                      | Overvoltage 59                                |
|                      | Undervoltage 27                               |
|                      | Positive sequence undervoltage 27P            |
|                      | Earth fault overvoltage 59N                   |
|                      | Underfrequency 81/81N                         |
|                      | Rate of change of frequency 81R               |
|                      | Synchro-check 25                              |
|                      | Lockout relay 86                              |
|                      | CT supervision 60                             |
|                      | VT supervision 60                             |
|                      | Programmable stages 99 8                      |
|                      | Programmable curve 99 8                       |
| <hr/>                |                                               |
| Arc flash protection | No                                            |

|                                 |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |
|---------------------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| measurement functions           | Current 3-phase<br>Current zero sequence<br>Current positive sequence<br>Current negative sequence<br>Current ratio of negative and positive<br>Voltage phase to earth<br>Voltage phase to phase<br>Voltage zero sequence<br>Voltage positive sequence<br>Voltage negative sequence<br>Voltage ratio of negative and positive<br>Short circuit fault reactance ratio of negative and positive<br>Fault location current<br>Earth fault reactance 3-phase<br>Frequency<br>Active power<br>RMS active power zero sequence<br>Frequency phasor diagram view<br>Reactive power ratio of negative and positive<br>RMS reactive power<br>Apparent power<br>RMS apparent power positive sequence<br>Active power 2nd, 15th harmonics with THD<br>Active energy ratio of negative and positive<br>Reactive energy phase to phase<br>Cos $\varphi$ zero sequence<br>Tan $\varphi$ negative sequence<br>Power angle<br>RMS active power 3-phase<br>Power factor<br>Voltage phasor diagram view<br>Current phasor diagram view<br>Current 2nd, 15th harmonics with THD<br>Voltage 2nd, 15th harmonics with THD<br>Condition monitoring CB wear<br>Voltage interruption<br>Reactive power zero sequence<br>RMS reactive power positive sequence<br>Apparent power negative sequence<br>RMS apparent power ratio of negative and positive<br>Active energy phase to earth<br>Reactive energy zero sequence<br>Cos $\varphi$ positive sequence<br>Tan $\varphi$ ratio of negative and positive |
| control functions               | Switchgear control and monitoring<br>Programmable switchgear interlocking<br>Local control on single-line diagram<br>Local control with I/O keys<br>Local/remote control<br>2 function keys<br>Mobile application with Easergy SmartApp<br>Web-server<br>Programmable logic                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| controllable switchgear devices | 4 controlled + 8 displayed                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                       |
| number of setting groups        | 4                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
| monitoring functions            | Trip circuit supervision 74<br>Circuit breaker monitoring<br>Relay self-monitoring                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| logs and records                | Event recording<br>Disturbance recording<br>Tripping context                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                     |
| Switchgear diagnosis type       | CT supervision TCS<br>Trip circuit supervision TCS                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| Connections - terminals         | Screw removable (digital input/output)<br>Pin removable (voltage transformer)<br>Pin removable (current transformer)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |

## Complementary

|                     |            |
|---------------------|------------|
| Operating threshold | 24 V AC/DC |
|---------------------|------------|

|                               |                                                                |
|-------------------------------|----------------------------------------------------------------|
| Time synchronisation protocol | SNTP                                                           |
| Software name                 | ESetup Easergy Pro virtual simulation test<br>Easergy SmartApp |
| Web server                    | Embedded HTTP server                                           |
| Display type                  | LCD 128 x 64 pixels with single line diagram                   |
| Number of key                 | 2 customizable                                                 |
| Local signalling              | 4 LEDs<br>8 LEDs programmable                                  |
| Height                        | 6.7 in (169.5 mm)                                              |
| Width                         | 6.7 in (170 mm)                                                |
| Depth                         | 8.07 in (205 mm)                                               |
| Net weight                    | 5.5 lb(US) (2.5 kg) maximum                                    |

## Environment

|                                       |                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
|---------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| climatic withstand                    | Exposure to dry heat Bb EN/IEC 60068-2-2<br>Exposure to cold Ad EN/IEC 60068-2-1<br>Exposure to damp heat in service Db EN/IEC 60068-2-30<br>Exposure to damp heat in service Cab EN/IEC 60068-2-78                                                                                                                                                                                                                                                                                                                                                             |
| Mechanical robustness                 | Vibrations class II) IEC 60255-21-1<br>VibrationsFc IEC 60068-2-6<br>Shocks class II) IEC 60255-21-2<br>ShocksEa IEC 60068-2-27<br>Seismic tests method A class II) IEC 60255-21-3                                                                                                                                                                                                                                                                                                                                                                              |
| Electromagnetic compatibility         | Emission tests IEC/EN 60255-26 ed. 3<br>Emission tests CISPR 11<br>Emission tests CISPR 22<br>EMC immunity IEC/EN 60255-26 ed. 3<br>EMC immunity EN/IEC 61000-4-18<br>EMC immunity level 4 EN/IEC 61000-4-2<br>EMC immunity level 3 EN/IEC 61000-4-3<br>EMC immunity level 4 EN/IEC 61000-4-4<br>EMC immunity level 3 EN/IEC 61000-4-5<br>EMC immunity level 3 EN/IEC 61000-4-6<br>EMC immunity EN/IEC 61000-4-8<br>EMC immunity level 5 EN/IEC 61000-4-9<br>EMC immunity EN/IEC 61000-4-29<br>EMC immunity EN/IEC 61000-4-11<br>EMC immunity EN/IEC 61000-4-17 |
| Ambient air temperature for operation | -40...149 °F (-40...65 °C)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| Ambient air temperature for storage   | -40...158 °F (-40...70 °C)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                      |
| IP degree of protection               | IP54 front IEC 60529                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                            |
| maximum operating altitude            | 6561.68 ft (2000 m)                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                             |
| Protective treatment                  | Conformal coating                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                               |
| Relative humidity                     | 0...95 %, without condensation                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                  |

## Ordering and shipping details

|                   |               |
|-------------------|---------------|
| Category          | US1PL1S11405  |
| Discount Schedule | PL1S          |
| GTIN              | 3606487107019 |
| Returnability     | No            |
| Country of origin | LV            |

## Packing Units

|                        |                         |
|------------------------|-------------------------|
| Unit Type of Package 1 | PCE                     |
| Nbr. of units in pkg.  | 1                       |
| Package 1 Height       | 9.700 in (24.638 cm)    |
| Package 1 Width        | 10.500 in (26.670 cm)   |
| Package 1 Length       | 12.200 in (30.988 cm)   |
| Package weight(Lbs)    | 7.370 lb(US) (3.343 kg) |

## Contractual warranty

|                      |    |
|----------------------|----|
| Warranty (in months) | 24 |
|----------------------|----|



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)



### Environmental footprint

|                                                        |                                               |
|--------------------------------------------------------|-----------------------------------------------|
| Total lifecycle Carbon footprint                       | 718 kg CO2 eq.                                |
| Carbon footprint of the manufacturing phase [A1 to A3] | 84 kg CO2 eq.                                 |
| Carbon footprint of the distribution phase [A4]        | 3 kg CO2 eq.                                  |
| Carbon footprint of the installation phase [A5]        | 0.1 kg CO2 eq.                                |
| Carbon footprint of the use phase [B2, B3, B4, B6]     | 624 kg CO2 eq.                                |
| Carbon footprint of the end-of-life phase [C1 to C4]   | 7 kg CO2 eq.                                  |
| Environmental Disclosure                               | <a href="#">Product Environmental Profile</a> |

## Use Better



### Materials and Substances

|                                        |                                                                                        |
|----------------------------------------|----------------------------------------------------------------------------------------|
| Packaging made with recycled cardboard | Yes                                                                                    |
| Packaging without single use plastic   | No                                                                                     |
| SCIP Number                            | 7fd15df9-a702-4a28-ad01-afb36a7b785f                                                   |
| EU RoHS Directive                      | <a href="#">Compliant By Exemption</a>                                                 |
| REACH Regulation                       | <a href="#">Reference contains Substances of Very High Concern above the threshold</a> |

## Use Longer



### Lifetime extension

|        |    |
|--------|----|
| Repair | No |
|--------|----|

## Use Again



### Repack and remanufacture

|                               |                                                                                                                                                                                                                  |
|-------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Recyclability potential, in % | 32                                                                                                                                                                                                               |
| Circularity Profile           | <a href="#">End of Life Information</a>                                                                                                                                                                          |
| Take-back                     | No                                                                                                                                                                                                               |
| WEEE Label                    |  The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins. |