

power contactor, AC-3e/AC-3, 32 A, 15 kW / 400 V, 3-pole, 400 V AC, 50 Hz / 400-440 V, 60 Hz, auxiliary contacts: 1 NO + 1 NC, spring-loaded terminal, size: S0

|  |                              |
|--|------------------------------|
| <b>product brand name</b>  | SIRIUS                       |
| <b>product designation</b>   | Power contactor              |
| <b>product type designation</b>  | 3RT2                         |
| <b>General technical data</b>  |                              |
| <b>size of contactor</b>   | S0                           |
| <b>product extension</b>   |                              |
| • function module for communication  | No                           |
| • auxiliary switch   | Yes                          |
| <b>power loss [W] for rated value of the current</b>   |                              |
| • at AC in hot operating state   | 6.3 W                        |
| • at AC in hot operating state per pole  | 2.3 W                        |
| • without load current share typical   | 2.7 W                        |
| <b>type of calculation of power loss current-dependent</b>   | quadratic                    |
| <b>insulation voltage</b>  |                              |
| • of main circuit with degree of pollution 3 rated value   | 690 V                        |
| • of auxiliary circuit with degree of pollution 3 rated value  | 690 V                        |
| <b>surge voltage resistance</b>  |                              |
| • of main circuit rated value  | 6 kV                         |
| • of auxiliary circuit rated value   | 6 kV                         |
| maximum permissible voltage for protective separation between coil and main contacts according to EN 60947-1 | 400 V                        |
| <b>shock resistance at rectangular impulse</b>   |                              |
| • at AC  | 8,3 g / 5 ms, 5,3 g / 10 ms  |
| <b>shock resistance with sine pulse</b>  |                              |
| • at AC  | 13,5 g / 5 ms, 8,3 g / 10 ms |
| <b>mechanical service life (operating cycles)</b>  |                              |
| • of contactor typical   | 10 000 000                   |
| • of the contactor with added electronically optimized auxiliary switch block typical                        | 5 000 000                    |
| • of the contactor with added auxiliary switch block typical   | 10 000 000                   |
| <b>reference code according to IEC 81346-2</b>   | Q                            |
| <b>Substance Prohibitance (day/month/year)</b>   | 10/01/2009                   |
| <b>Net Weight</b>  | 0.45 g                       |
| <b>Ambient conditions</b>  |                              |
| installation altitude at height above sea level maximum  | 2 000 m                      |
| <b>ambient temperature</b>   |                              |
| • during operation   | -25 ... +60 °C               |
| • during storage   | -55 ... +80 °C               |
| <b>relative humidity minimum</b>   | 10 %                         |
| <b>relative humidity at 55 °C according to IEC 60068-2-30 maximum</b>  | 95 %                         |
| <b>Main circuit</b>  |                              |
| <b>number of poles for main current circuit</b>  | 3                            |
| <b>number of NO contacts for main contacts</b>   | 3                            |
| <b>number of NC contacts for main contacts</b>   | 0                            |
| <b>operating voltage</b>   |                              |
| • at AC-3 rated value maximum  | 690 V                        |
| • at AC-3e rated value maximum   | 690 V                        |
| <b>operational current</b>   |                              |
| • at AC-1 at 400 V at ambient temperature 40 °C rated  | 50 A                         |

|   |                    |
|---|--------------------|
| value   |                    |
| <ul style="list-style-type: none"> <li>● at AC-1 <ul style="list-style-type: none"> <li>— up to 690 V at ambient temperature 40 °C rated value 50 A</li> <li>— up to 690 V at ambient temperature 60 °C rated value 42 A</li> </ul> </li> <li>● at AC-3 <ul style="list-style-type: none"> <li>— at 400 V rated value 32 A</li> <li>— at 500 V rated value 32 A</li> <li>— at 690 V rated value 21 A</li> </ul> </li> <li>● at AC-3e <ul style="list-style-type: none"> <li>— at 400 V rated value 32 A</li> <li>— at 500 V rated value 32 A</li> <li>— at 690 V rated value 21 A</li> </ul> </li> <li>● at AC-4 at 400 V rated value 22 A</li> <li>● at AC-5a up to 690 V rated value 44 A</li> <li>● at AC-5b up to 400 V rated value 26.5 A</li> <li>● at AC-6a <ul style="list-style-type: none"> <li>— up to 230 V for current peak value n=20 rated value 30.8 A</li> <li>— up to 400 V for current peak value n=20 rated value 30.8 A</li> <li>— up to 500 V for current peak value n=20 rated value 27 A</li> <li>— up to 690 V for current peak value n=20 rated value 21 A</li> </ul> </li> <li>● at AC-6a <ul style="list-style-type: none"> <li>— up to 230 V for current peak value n=30 rated value 20.5 A</li> <li>— up to 400 V for current peak value n=30 rated value 20.5 A</li> <li>— up to 500 V for current peak value n=30 rated value 18 A</li> <li>— up to 690 V for current peak value n=30 rated value 18 A</li> </ul> </li> </ul> |                    |
| minimum cross-section in main circuit at maximum AC-1 rated value   | 10 mm <sup>2</sup> |
| <b>operational current for approx. 200000 operating cycles at AC-4</b>  |                    |
| <ul style="list-style-type: none"> <li>● at 400 V rated value 12 A</li> <li>● at 690 V rated value 12 A</li> </ul>  |                    |
| <b>operational current</b>  |                    |
| <ul style="list-style-type: none"> <li>● <b>at 1 current path at DC-1</b> <ul style="list-style-type: none"> <li>— at 24 V rated value 35 A</li> <li>— at 60 V rated value 20 A</li> <li>— at 110 V rated value 4.5 A</li> <li>— at 220 V rated value 1 A</li> <li>— at 440 V rated value 0.4 A</li> <li>— at 600 V rated value 0.25 A</li> </ul> </li> <li>● <b>with 2 current paths in series at DC-1</b> <ul style="list-style-type: none"> <li>— at 24 V rated value 35 A</li> <li>— at 60 V rated value 35 A</li> <li>— at 110 V rated value 35 A</li> <li>— at 220 V rated value 5 A</li> <li>— at 440 V rated value 1 A</li> <li>— at 600 V rated value 0.8 A</li> </ul> </li> <li>● <b>with 3 current paths in series at DC-1</b> <ul style="list-style-type: none"> <li>— at 24 V rated value 35 A</li> <li>— at 60 V rated value 35 A</li> <li>— at 110 V rated value 35 A</li> <li>— at 220 V rated value 35 A</li> <li>— at 440 V rated value 2.9 A</li> <li>— at 600 V rated value 1.4 A</li> </ul> </li> <li>● <b>at 1 current path at DC-3 at DC-5</b> <ul style="list-style-type: none"> <li>— at 24 V rated value 20 A</li> <li>— at 60 V rated value 5 A</li> <li>— at 220 V rated value 1 A</li> <li>— at 440 V rated value 0.09 A</li> </ul> </li> </ul>  |                    |

|  |   |
|--|---|
| <ul style="list-style-type: none"> <li>— at 600 V rated value</li> </ul>   | 0.06 A  |
| <ul style="list-style-type: none"> <li>● <b>with 2 current paths in series at DC-3 at DC-5</b> <ul style="list-style-type: none"> <li>— at 24 V rated value</li> <li>— at 60 V rated value</li> <li>— at 110 V rated value</li> <li>— at 220 V rated value</li> <li>— at 440 V rated value</li> <li>— at 600 V rated value</li> </ul> </li> <li>● <b>with 3 current paths in series at DC-3 at DC-5</b> <ul style="list-style-type: none"> <li>— at 24 V rated value</li> <li>— at 60 V rated value</li> <li>— at 110 V rated value</li> <li>— at 220 V rated value</li> <li>— at 440 V rated value</li> <li>— at 600 V rated value</li> </ul> </li> </ul> | 35 A<br>35 A<br>15 A<br>3 A<br>0.27 A<br>0.16 A<br><br>35 A<br>35 A<br>35 A<br>10 A<br>0.6 A<br>0.6 A   |
| <b>operating power</b> <ul style="list-style-type: none"> <li>● at AC-2 at 400 V rated value</li> <li>● at AC-3               <ul style="list-style-type: none"> <li>— at 230 V rated value</li> <li>— at 400 V rated value</li> <li>— at 500 V rated value</li> <li>— at 690 V rated value</li> </ul> </li> <li>● at AC-3e               <ul style="list-style-type: none"> <li>— at 230 V rated value</li> <li>— at 400 V rated value</li> <li>— at 500 V rated value</li> <li>— at 690 V rated value</li> </ul> </li> </ul>   | 15 kW<br><br>7.5 kW<br>15 kW<br>15 kW<br>18.5 kW<br><br>7.5 kW<br>15 kW<br>15 kW<br>18.5 kW   |
| <b>operating power for approx. 200000 operating cycles at AC-4</b> <ul style="list-style-type: none"> <li>● at 400 V rated value</li> <li>● at 690 V rated value</li> </ul>  | 6 kW<br>10.3 kW   |
| <b>operating apparent power at AC-6a</b> <ul style="list-style-type: none"> <li>● up to 230 V for current peak value n=20 rated value</li> <li>● up to 400 V for current peak value n=20 rated value</li> <li>● up to 500 V for current peak value n=20 rated value</li> <li>● up to 690 V for current peak value n=20 rated value</li> </ul>  | 12.2 kVA<br>21.3 kVA<br>23.3 kVA<br>25 kVA  |
| <b>operating apparent power at AC-6a</b> <ul style="list-style-type: none"> <li>● up to 230 V for current peak value n=30 rated value</li> <li>● up to 400 V for current peak value n=30 rated value</li> <li>● up to 500 V for current peak value n=30 rated value</li> <li>● up to 690 V for current peak value n=30 rated value</li> </ul>  | 8.1 kVA<br>14.2 kVA<br>15.5 kVA<br>21.5 kVA   |
| <b>short-time withstand current in cold operating state up to 40 °C</b> <ul style="list-style-type: none"> <li>● limited to 1 s switching at zero current maximum</li> <li>● limited to 5 s switching at zero current maximum</li> <li>● limited to 10 s switching at zero current maximum</li> <li>● limited to 30 s switching at zero current maximum</li> <li>● limited to 60 s switching at zero current maximum</li> </ul>  | 499 A; Use minimum cross-section acc. to AC-1 rated value<br>341 A; Use minimum cross-section acc. to AC-1 rated value<br>260 A; Use minimum cross-section acc. to AC-1 rated value<br>199 A; Use minimum cross-section acc. to AC-1 rated value<br>162 A; Use minimum cross-section acc. to AC-1 rated value |
| <b>no-load switching frequency</b> <ul style="list-style-type: none"> <li>● at AC</li> </ul>   | 5 000 1/h   |
| <b>operating frequency</b> <ul style="list-style-type: none"> <li>● at AC-1 maximum</li> <li>● at AC-2 maximum</li> <li>● at AC-3 maximum</li> <li>● at AC-3e               <ul style="list-style-type: none"> <li>— maximum</li> </ul> </li> <li>● at AC-4 maximum</li> </ul>   | 1 000 1/h<br>750 1/h<br>750 1/h<br><br>750 1/h<br>250 1/h   |
| <b>Control circuit/ Control</b>  |   |
| type of voltage of the control supply voltage  | AC  |

|   |   |
|---|---|
| <b>control supply voltage at AC</b>   |   |
| • at 50 Hz rated value  | 400 V   |
| • at 60 Hz rated value  | 400 ... 440 V                                   |
| <b>operating range factor control supply voltage rated value of magnet coil at AC</b> |   |
| • at 50 Hz  | 0.8 ... 1.1                                     |
| • at 60 Hz  | 0.8 ... 1.1                                     |
| <b>apparent pick-up power of magnet coil at AC</b>                                    |   |
| • at 50 Hz  | 81 VA   |
| • at 60 Hz  | 79 VA   |
| <b>inductive power factor with closing power of the coil</b>                          |   |
| • at 50 Hz  | 0.72  |
| • at 60 Hz  | 0.74  |
| <b>apparent holding power</b>   |   |
| • at minimum rated control supply voltage at AC<br>— at 60 Hz                         | 10.5 VA   |
| • at maximum rated control supply voltage at AC<br>— at 60 Hz                         | 8.5 VA  |
| <b>apparent holding power of magnet coil at AC</b>                                    |   |
| • at 50 Hz  | 10.5 VA   |
| • at 60 Hz  | 8.5 VA  |
| <b>inductive power factor with the holding power of the coil</b>                      |   |
| • at 50 Hz  | 0.25  |
| • at 60 Hz  | 0.28  |
| <b>closing delay</b>  |   |
| • at AC   | 8 ... 40 ms                                     |
| <b>opening delay</b>  |   |
| • at AC   | 4 ... 16 ms                                     |
| <b>arcing time</b>  | 10 ms   |
| <b>control version of the switch operating mechanism</b>                              | Standard A1 - A2                                |
| <b>Auxiliary circuit</b>  |   |
| number of NC contacts for auxiliary contacts instantaneous contact                    | 1   |
| number of NO contacts for auxiliary contacts instantaneous contact                    | 1   |
| operational current at AC-12 maximum  | 10 A  |
| <b>operational current at AC-15</b>   |   |
| • at 230 V rated value  | 10 A  |
| • at 400 V rated value  | 3 A   |
| • at 500 V rated value  | 2 A   |
| • at 690 V rated value  | 1 A   |
| <b>operational current at DC-12</b>   |   |
| • at 24 V rated value   | 10 A  |
| • at 48 V rated value   | 6 A   |
| • at 60 V rated value   | 6 A   |
| • at 110 V rated value  | 3 A   |
| • at 125 V rated value  | 2 A   |
| • at 220 V rated value  | 1 A   |
| • at 600 V rated value  | 0.15 A  |
| <b>operational current at DC-13</b>   |   |
| • at 24 V rated value   | 10 A  |
| • at 48 V rated value   | 2 A   |
| • at 60 V rated value   | 2 A   |
| • at 110 V rated value  | 1 A   |
| • at 125 V rated value  | 0.9 A   |
| • at 220 V rated value  | 0.3 A   |
| • at 600 V rated value  | 0.1 A   |
| <b>contact reliability of auxiliary contacts</b>                                      | 1 faulty switching per 100 million (17 V, 1 mA) |
| <b>UL/CSA ratings</b>   |   |
| <b>full-load current (FLA) for 3-phase AC motor</b>                                   |   |

|   |   |
|---|---|
| <ul style="list-style-type: none"> <li>• at 480 V rated value</li> <li>• at 600 V rated value</li> </ul>  | <p>27 A</p> <p>27 A</p>   |
| <b>yielded mechanical performance [hp]</b> <ul style="list-style-type: none"> <li>• for single-phase AC motor <ul style="list-style-type: none"> <li>— at 110/120 V rated value</li> <li>— at 230 V rated value</li> </ul> </li> <li>• for 3-phase AC motor <ul style="list-style-type: none"> <li>— at 200/208 V rated value</li> <li>— at 220/230 V rated value</li> <li>— at 460/480 V rated value</li> <li>— at 575/600 V rated value</li> </ul> </li> </ul>  | <p>2 hp</p> <p>5 hp</p> <p>10 hp</p> <p>10 hp</p> <p>20 hp</p> <p>25 hp</p>   |
| <b>contact rating of auxiliary contacts according to UL</b>   | A600 / P600   |
| <b>UL File Number (CCN)</b>   | E31519 (NLDX, NLDX7)  |
| <b>Short-circuit protection</b>   |   |
| design of the miniature circuit breaker for short-circuit protection of the auxiliary circuit up to 230 V   | C characteristic: 10 A; 0.4 kA  |
| <b>design of the fuse link</b> <ul style="list-style-type: none"> <li>• for short-circuit protection of the main circuit <ul style="list-style-type: none"> <li>— with type of coordination 1 required</li> <li>— with type of coordination 2 required</li> </ul> </li> <li>• for short-circuit protection of the auxiliary switch required</li> </ul>  | <p>gG: 125 A (690 V, 100 kA), aM: 50 A (690 V, 100 kA), BS88: 125 A (415 V, 80 kA)</p> <p>gG: 50 A (690 V, 100 kA), aM: 25 A (690 V, 100 kA), BS88: 50 A (415 V, 80 kA)</p> <p>gG: 10 A (500 V, 1 kA)</p> |
| <b>Installation/ mounting/ dimensions</b>   |   |
| <b>mounting position</b>  | +/-180° rotation possible on vertical mounting surface; can be tilted forward and backward by +/- 22.5° on vertical mounting surface  |
| fastening method side-by-side mounting  | Yes   |
| <b>fastening method</b>   | screw and snap-on mounting onto 35 mm DIN rail according to DIN EN 60715  |
| <b>height</b>   | 102 mm  |
| <b>width</b>  | 45 mm   |
| <b>depth</b>  | 97 mm   |
| <b>required spacing</b> <ul style="list-style-type: none"> <li>• with side-by-side mounting <ul style="list-style-type: none"> <li>— forwards</li> <li>— upwards</li> <li>— downwards</li> <li>— at the side</li> </ul> </li> <li>• for grounded parts <ul style="list-style-type: none"> <li>— forwards</li> <li>— upwards</li> <li>— at the side</li> <li>— downwards</li> </ul> </li> <li>• for live parts <ul style="list-style-type: none"> <li>— forwards</li> <li>— upwards</li> <li>— downwards</li> <li>— at the side</li> </ul> </li> </ul> | <p>10 mm</p> <p>10 mm</p> <p>10 mm</p> <p>0 mm</p> <p>10 mm</p> <p>10 mm</p> <p>6 mm</p> <p>10 mm</p> <p>10 mm</p> <p>10 mm</p> <p>10 mm</p> <p>6 mm</p>  |
| <b>Connections/ Terminals</b>   |   |
| <b>type of electrical connection</b> <ul style="list-style-type: none"> <li>• for main current circuit</li> <li>• for auxiliary and control circuit</li> <li>• at contactor for auxiliary contacts</li> <li>• of magnet coil</li> </ul>   | <p>spring-loaded terminals</p> <p>spring-loaded terminals</p> <p>Spring-type terminals</p> <p>Spring-type terminals</p>   |
| <b>type of connectable conductor cross-sections</b> <ul style="list-style-type: none"> <li>• for main contacts <ul style="list-style-type: none"> <li>— solid</li> <li>— solid or stranded</li> <li>— finely stranded with core end processing</li> <li>— finely stranded without core end processing</li> </ul> </li> <li>• for AWG cables for main contacts</li> </ul>  | <p>2x (1 ... 10 mm<sup>2</sup>)</p> <p>2x (1 ... 10 mm<sup>2</sup>)</p> <p>2x (1 ... 6 mm<sup>2</sup>)</p> <p>2x (1 ... 6 mm<sup>2</sup>)</p> <p>2x (18 ... 8)</p>  |
| <b>connectable conductor cross-section for main contacts</b>  |   |

|   |                                   |
|---|-----------------------------------|
| <ul style="list-style-type: none"> <li>• solid</li> </ul>   | 1 ... 10 mm <sup>2</sup>          |
| <ul style="list-style-type: none"> <li>• stranded</li> </ul>  | 1 ... 10 mm <sup>2</sup>          |
| <ul style="list-style-type: none"> <li>• finely stranded with core end processing</li> </ul>  | 1 ... 6 mm <sup>2</sup>           |
| <ul style="list-style-type: none"> <li>• finely stranded without core end processing</li> </ul>   | 1 ... 6 mm <sup>2</sup>           |
| <b>connectable conductor cross-section for auxiliary contacts</b>   |                                   |
| <ul style="list-style-type: none"> <li>• solid or stranded</li> </ul>   | 0.5 ... 2.5 mm <sup>2</sup>       |
| <ul style="list-style-type: none"> <li>• finely stranded with core end processing</li> </ul>  | 0.5 ... 1.5 mm <sup>2</sup>       |
| <ul style="list-style-type: none"> <li>• finely stranded without core end processing</li> </ul>   | 0.5 ... 2.5 mm <sup>2</sup>       |
| <b>type of connectable conductor cross-sections</b>   |                                   |
| <ul style="list-style-type: none"> <li>• for auxiliary contacts <ul style="list-style-type: none"> <li>— solid or stranded</li> </ul> </li> </ul> | 2x (0.5 ... 2.5 mm <sup>2</sup> ) |
| <ul style="list-style-type: none"> <li>— finely stranded with core end processing</li> </ul>  | 2x (0.5 ... 1.5 mm <sup>2</sup> ) |
| <ul style="list-style-type: none"> <li>— finely stranded without core end processing</li> </ul>   | 2x (0.5 ... 2.5 mm <sup>2</sup> ) |
| <ul style="list-style-type: none"> <li>• for AWG cables for auxiliary contacts</li> </ul>   | 2x (20 ... 14)                    |
| <b>AWG number as coded connectable conductor cross section for main contacts</b>  | 18 ... 8                          |
| <b>AWG number as coded connectable conductor cross section for auxiliary contacts</b>   | 20 ... 14                         |

#### Safety related data

|  |  |
|--|--|
| <b>product function</b>  |  |
| <ul style="list-style-type: none"> <li>• mirror contact according to IEC 60947-4-1</li> </ul>              | Yes  |
| <ul style="list-style-type: none"> <li>• positively driven operation according to IEC 60947-5-1</li> </ul> | No   |
| <ul style="list-style-type: none"> <li>• suitable for safety function</li> </ul>                           | Yes  |
| suitability for use safety-related switching OFF   | Yes  |
| <b>service life maximum</b>  | 20 a   |
| <b>test wear-related service life necessary</b>  | Yes  |
| <b>proportion of dangerous failures</b>  |  |
| <ul style="list-style-type: none"> <li>• with low demand rate according to SN 31920</li> </ul>             | 40 %   |
| <ul style="list-style-type: none"> <li>• with high demand rate according to SN 31920</li> </ul>            | 73 %   |
| <b>B10 value with high demand rate according to SN 31920</b>   | 1 000 000  |
| <b>failure rate [FIT] with low demand rate according to SN 31920</b>                                       | 100 FIT  |
| <b>ISO 13849</b>   |  |
| <b>device type according to ISO 13849-1</b>  | 3  |
| <b>overdimensioning according to ISO 13849-2 necessary</b>   | Yes  |
| <b>IEC 61508</b>   |  |
| <b>safety device type according to IEC 61508-2</b>   | Type A   |
| <b>Electrical Safety</b>   |  |
| <b>protection class IP on the front according to IEC 60529</b>   | IP20   |
| <b>touch protection on the front according to IEC 60529</b>  | finger-safe, for vertical contact from the front |

#### Further information

##### Information on the packaging

<https://support.industry.siemens.com/cs/ww/en/view/109813875>

##### Information for data generation and storage

<https://support.industry.siemens.com/cs/ww/en/view/109995012>

##### Information- and Downloadcenter (Catalogs, Brochures,...)

<https://www.siemens.com/ic10>

##### Industry Mall (Online ordering system)

<https://mall.industry.siemens.com/mall/en/en/Catalog/product?mlfb=3RT2027-2AR60>

##### Service&Support (Manuals, Certificates, Characteristics, FAQs,...)

<https://support.industry.siemens.com/cs/ww/en/ps/3RT2027-2AR60>

##### Image database (product images, 2D dimension drawings, 3D models, device circuit diagrams, EPLAN macros, ...)

[https://www.automation.siemens.com/bilddb/cax\\_de.aspx?mlfb=3RT2027-2AR60&lang=en](https://www.automation.siemens.com/bilddb/cax_de.aspx?mlfb=3RT2027-2AR60&lang=en)

##### Cax online generator

<https://support.automation.siemens.com/WW/CAXorder/default.aspx?lang=en&mlfb=3RT2027-2AR60>

##### Characteristic curves

[https://curves.simaris.siemens.com/curves/<mmp\\_prod\\_noCOMP="HAUPT"></mmp\\_prod\\_no>](https://curves.simaris.siemens.com/curves/<mmp_prod_noCOMP=)

last modified:

4/4/2026 