

Product datasheet

Specifications



Programmable contacts M2C,
MasterPact NW drawout, 2 NO/NC
contacts 5A/240VAC, for MicroLogic
P/H only

48382

Main

Range of product	Masterpact UR MasterPact NW MasterPact NW UL 489
Range	MasterPact
Device short name	M2c
Product or component type	Programmable contact
Device application	Control
Range compatibility	Masterpact MasterPact NW circuit breaker Masterpact MasterPact NW UL 489 circuit breaker Masterpact Masterpact UR circuit breaker

Complementary

Mounting mode	Drawout
[Ie] rated operational current	1.5 A at 48 V DC 1.8 A at 24 V DC 3 A at 380 V AC 5 A at 240 V AC 0.15 A at 250 V DC 0.4 A at 125 V DC
Minimum load	100 mA at 24 V

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.5 cm
Package 1 Width	6.0 cm
Package 1 Length	8.2 cm
Package 1 Weight	70.0 g

Logistical informations

Country of origin	FR
-------------------	----

Contractual warranty

Warranty (in months)	18
----------------------	----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
SCIP Number	7ad12b2f-38d8-4da7-8519-e4f93e0ce077
EU RoHS Directive	Compliant By Exemption
REACH Regulation	Reference contains Substances of Very High Concern above the threshold

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
Take-back	Yes
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins