

# Product datasheet

Specifications



## AC servo motors BRH - 4.2 N.m - 6000 rpm - untapped shaft - with brake - IP41

BRH0851P01F1A

### Main

<b>Product or component type</b>	Motion servo motors
<b>Component name</b>	BRH
<b>Continuous stall torque</b>	1.86 N.m
<b>Peak stall torque</b>	4.61 N.m for LXM05AD17F1 4.61 N.m for LXM05AD17M2 4.61 N.m for LXM05AD17M3X 4.61 N.m for LXM05BD17F1 4.61 N.m for LXM05BD17M2 4.61 N.m for LXM05BD17M3X 4.61 N.m for LXM05CD17F1 4.61 N.m for LXM05CD17M2 4.61 N.m for LXM05CD17M3X 5.34 N.m for LXM05AD22N4 5.34 N.m for LXM05BD22N4 5.34 N.m for LXM05CD22N4
<b>Nominal output power</b>	280 W for LXM05AD17F1 280 W for LXM05BD17F1 280 W for LXM05CD17F1 730 W for LXM05AD17M2 730 W for LXM05AD17M3X 730 W for LXM05BD17M2 730 W for LXM05BD17M3X 730 W for LXM05CD17M2 730 W for LXM05CD17M3X 910 W for LXM05AD22N4 910 W for LXM05BD22N4 910 W for LXM05CD22N4
<b>Nominal speed</b>	1500 rpm for LXM05AD17F1 1500 rpm for LXM05BD17F1 1500 rpm for LXM05CD17F1 4500 rpm for LXM05AD17M2 4500 rpm for LXM05AD17M3X 4500 rpm for LXM05BD17M2 4500 rpm for LXM05BD17M3X 4500 rpm for LXM05CD17M2 4500 rpm for LXM05CD17M3X 6000 rpm for LXM05AD22N4 6000 rpm for LXM05BD22N4 6000 rpm for LXM05CD22N4
<b>Maximum mechanical speed</b>	6000 rpm
<b>Product compatibility</b>	LXM05AD17F1 at 115 V single phase LXM05AD17M2 at 230 V single phase LXM05AD17M3X at 230 V 3 phases LXM05AD22N4 at 400/480 V 3 phases LXM05BD17F1 at 115 V single phase LXM05BD17M2 at 230 V single phase LXM05BD17M3X at 230 V 3 phases LXM05BD22N4 at 400/480 V 3 phases LXM05CD17F1 at 115 V single phase LXM05CD17M2 at 230 V single phase LXM05CD17M3X at 230 V 3 phases LXM05CD22N4 at 400/480 V 3 phases
<b>Shaft end</b>	Untapped

<b>IP degree of protection</b>	IP41
<b>Encoder type</b>	Single turn SinCos Hiperface
<b>Speed feedback resolution</b>	131072 points/turn
<b>Holding brake</b>	With
<b>Mounting support</b>	International standard flange
<b>Electrical connection</b>	Straight connectors
<b>Nominal torque</b>	1.45 N.m for LXM05AD22N4 1.45 N.m for LXM05BD22N4 1.45 N.m for LXM05CD22N4 1.55 N.m for LXM05AD17M2 1.55 N.m for LXM05AD17M3X 1.55 N.m for LXM05BD17M2 1.55 N.m for LXM05BD17M3X 1.55 N.m for LXM05CD17M2 1.55 N.m for LXM05CD17M3X 1.76 N.m for LXM05AD17F1 1.76 N.m for LXM05BD17F1 1.76 N.m for LXM05CD17F1
<b>Number of poles</b>	10
<b>Maximum radial force Fr</b>	173 N at 6000 rpm 176 N at 5000 rpm 181 N at 4000 rpm 187 N at 3000 rpm 193 N at 2000 rpm 226 N at 1000 rpm

## Complementary

<b>Range compatibility</b>	Lexium 05
<b>Switching frequency</b>	8 kHz
<b>Maximum current Irms</b>	11 A for LXM05AD17F1 11 A for LXM05AD17M2 11 A for LXM05AD17M3X 11 A for LXM05BD17F1 11 A for LXM05BD17M2 11 A for LXM05BD17M3X 11 A for LXM05CD17F1 11 A for LXM05CD17M2 11 A for LXM05CD17M3X 14 A for LXM05AD22N4 14 A for LXM05BD22N4 14 A for LXM05CD22N4
<b>Torque constant</b>	0.48 N.m/A at 120 °C
<b>Back emf constant</b>	30.5 V/krpm at 120 °C
<b>Rotor inertia</b>	1.06 kg.cm <sup>2</sup> without brake 1.59 kg.cm <sup>2</sup> with brake
<b>Stator resistance</b>	2.1 Ohm
<b>Stator inductance</b>	8 mH
<b>Stator electrical time constant</b>	3.8 ms
<b>Maximum axial force Fa</b>	0.2 x Fr
<b>Net weight</b>	2.2 kg

## Contractual warranty

<b>Warranty (in months)</b>	18
-----------------------------	----



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Longer



#### Lifetime extension

Repair

No