

Product datasheet

Specifications



DOL reversing combination starter - TeSys GV2-ME - 9...14 A - 110 V AC

GV2ME16K2F7

EAN Code: 3389110949889

❗ Discontinued

Main

Range	TeSys
Device short name	GV2ME
Product or component type	Motor starter
Motor starter type	Reversing
Poles description	3P
Utilisation category	AC-3
Motor power kW	5.5 kW at 400/415 V AC 50/60 Hz 5.5 kW at 440 V AC 50/60 Hz 7.5 kW at 500 V AC 50/60 Hz
[Uc] control circuit voltage	110 V AC 50/60 Hz
thermal protection adjustment range	9...14 A
Magnetic tripping current	170 A

Complementary

Device composition	1 combination block GV2AF01 1 motor circuit breaker type GV2ME 1 3-pole reversing contactor
Coordination type	Type 1
Breaking capacity	15 kA Iq at 400/415 V AC 50/60 Hz conforming to IEC 60947-4-1 8 kA Iq at 440 V AC 50/60 Hz conforming to IEC 60947-4-1 6 kA Iq at 500 V AC 50/60 Hz conforming to IEC 60947-4-1
Net weight	0.46 kg
Height	152 mm
Width	45 mm
Depth	87 mm

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins