

Product datasheet

Specifications



Auxiliary contacts, TeSys GS, 1 C/O, early break, side mounting, for GS1 32A with direct front/right handle

GS1AM111

⚠ Discontinued on: 1 Dec 2024

⚠ To be discontinued

Main

Range of product	TeSys
Device short name	GS1AM
Product or component type	Auxiliary contact
Contact application	O and I position signalling
Range compatibility	TeSys TeSys GS GS1D fuse-switch disconnecter
Contacts type and composition	1 C/O
Contact operation	Early-break
[I _{th}] conventional free air thermal current	16 A (at 40 °C)
[I _e] rated operational current	5 A at 127 V AC-15 4 A at 230 V AC-15 3 A at 400/415 V AC-15 2 A at 440 V AC-15 12 A at 24 V DC-13 2 A at 48 V DC-13 0.6 A at 110 V DC-13 0.4 A at 220 V DC-13

Complementary

Mechanical durability	1 Mcycles
Electrical durability	30000 cycles AC-15
switch rated current	32 A
Fuse type	NFC DIN BS
Type of operating handle	Direct frontal
Mounting location	Right side

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	12 cm
Package 1 Width	8 cm
Package 1 Length	3 cm
Package 1 Weight	75 g
Unit Type of Package 2	S01

Excluding VAT, FCA Jabal Ali & amp; are subject to change – check with your local distributor.

Number of Units in Package 2	15
Package 2 Height	15 cm
Package 2 Width	15 cm
Package 2 Length	40 cm
Package 2 Weight	1.304 kg

Contractual warranty

Warranty (in months)	18
-----------------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better



Materials and Substances

Packaging made with recycled cardboard

Yes

Packaging without single use plastic

Yes

EU RoHS Directive

[Compliant](#)

REACH Regulation

[Free of Substances of Very High Concern above the threshold](#)

Use Longer



Lifetime extension

Repair

No

Use Again



Repack and remanufacture

Take-back

Nej

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins