

Product datasheet

Specifications



Auxiliary contacts, TeSys GS, 2NC+2NO, instantaneous, right side mounting, for GS2 with left handle

GS1AN22G

⚠ Discontinued on: Feb 27, 2026

⚠ Discontinued

Main

Range of product	TeSys
Device short name	GS1AN
Product or component type	Auxiliary contact
Contact application	O and I position signalling
Contacts type and composition	2 NO + 2 NC
Contact operation	Instantaneous
[Ith] conventional free air thermal current	20 A (at 40 °C)
[Ie] rated operational current	1 A at 220 V DC-13 10 A at 230 V AC-15 12 A at 127 V AC-15 4 A at 48 V DC-13 6 A at 440 V AC-15 8 A at 400/415 V AC-15 1.2 A at 110 V DC-13

Complementary

Range compatibility	TeSys TeSys GS fuse-switch disconnecter
Mechanical durability	30000 cycles
Electrical durability	30000 cycles AC-15
switch rated current	100 A 125 A 160 A 60 A 400 A 600 A 800 A 200 A 630 A 250 A 315 A 50 A 63 A 1250 A
Fuse type	DIN BS NFC
Type of operating handle	External left side
Product weight	0.252 kg

Packing Units

Unit Type of Package 1	PCE
------------------------	-----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Number of Units in Package 1	1
Package 1 Height	7.0 cm
Package 1 Width	4.5 cm
Package 1 Length	13.0 cm
Package 1 Weight	217.0 g

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)



Environmental footprint

Environmental Disclosure

[Product Environmental Profile](#)

Use Better



Materials and Substances

Packaging made with recycled cardboard

Yes

Packaging without single use plastic

No

EU RoHS Directive

[Compliant](#)

Use Longer



Lifetime extension

Repair

No

Use Again



Repack and remanufacture

End of life manual availability

[End of Life Information](#)

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins