


Product datasheet

Specifications



contactor coil - TeSys F - LX1FL - 200..220 V AC 40...400 Hz

LX1FL2206

⚠ Discontinued on: 1 Nov 2020

⚠ Discontinued

Main

Range	TeSys
Product or component type	Contactor coil
Device short name	LX1FL
Range compatibility	TeSys TeSys F LC1F contactor
Product compatibility	LC1F630 LC1F1250
Control circuit type	AC at 40...400 Hz
[Uc] control circuit voltage	200...220 V AC 40...400 Hz
Operating time	100...200 ms opening 40...80 ms closing
Mechanical durability	5 Mcycles
Maximum operating rate	1200 cyc/h 55 °C

Complementary

Coil technology	Without built-in suppressor module
-----------------	------------------------------------

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	10.0 cm
Package 1 Width	12.0 cm
Package 1 Length	22.5 cm
Package 1 Weight	1.45 kg

Contractual warranty

Warranty (in months)	18
----------------------	----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
SCIP Number	975ba4d0-bc82-40e2-8faa-6f6819f63b0c
EU RoHS Directive	Compliant By Exemption
REACH Regulation	Reference contains Substances of Very High Concern above the threshold

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
End of life manual availability	End of Life Information
Take-back	No
WEEE Label	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins