

# Product datasheet

Specifications



## TeSys Integral - shunt trip - 120 V AC 60 Hz - without time delay

LA1LC071FC

⚠ Discontinued on: 1 Nov 2020

⚠ Discontinued

### Main

Range	TeSys
Device short name	LA1LC
Product or component type	Shunt trip
Product compatibility	LD5 LD4
Range compatibility	TeSys TeSys Integral contactor breaker

### Complementary

[Uc] control circuit voltage	120 V AC 60 Hz
Time delay	Without time delay
Voltage release type	Instantaneous Shunt trip
Control circuit voltage limits	0.7...1.1 Uc
Threshold tripping voltage	0.35...0.7 Uc
Inrush power in VA	8 VA AC
Hold-in power consumption in VA	4 VA AC
Operating time	>= 10 ms
Quantity per set	Set of 10
Net weight	0.15 kg

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4 cm
Package 1 Width	5 cm
Package 1 Length	11.5 cm
Package 1 Weight	0.17 kg

### Contractual warranty

Warranty (in months)	18
----------------------	----



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Longer



#### Lifetime extension

Repair

No