

Product data sheet

Specifications



TeSys LE - enclosure for DOL starter - with selector switch and pushbutton

DE2DS2

⚠ Discontinued on: Jan 12, 2023

⚠ Discontinued

Main

Range of product	TeSys
Range	TeSys
Device short name	DE2D
Product or component type	Enclosure
Material	Polycarbonate
Device composition	Contactors ordered separately Thermal overload relay ordered separately
Product compatibility	LE2D09...35
Control type	Push-button reset blue R Selector switch 2 positions start/stop O-I

Complementary

Cable entry number	2 ISO20 top 2 ISO20 bottom 2 Pg 16 bottom 2 ISO25 top 2 Pg 21 bottom 2 ISO25 bottom
Height	201 mm
Width	103 mm
Depth	160 mm
Net weight	0.5 kg

Environment

IP degree of protection	IP65 conforming to IEC 60529
IK degree of protection	IK07 conforming to IEC 60529
Ambient air temperature for operation	-5...40 °C
Environmental characteristic	Standard environment
Product certifications	UKCA

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	15.0 cm

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Package 1 Width	16.0 cm
Package 1 Length	21.0 cm
Package 1 Weight	0.661 kg

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
EU RoHS Directive	Compliant

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
End of life manual availability	No need of specific recycling operations
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins