

Introduction

Schneider Electric PowerLogic High Accuracy and Split-Core Current Transducers (CTs) provide secondary voltage AC proportional to the primary (sensed) current. For use with the HDPM6000 platform only, these CTs provide a means to transform electrical service amperages to a voltage compatible with monitoring equipment.

These CTs range from 20A to 4000A voltage ratings with 0.2% to 1% accuracy.

Ordering Information

Model Number	Description	Accuracy
SUN2		
METSEHDPM20A12H	20A, High Accuracy Split-Core CT, 12' lead	0.2%
METSEHDPM20A30H	20A, High Accuracy Split-Core CT, 30' lead	0.2%
SUN3		
METSEHDPM75A12H	75A, High Accuracy Split-Core CT, 12' lead	0.2%
METSEHDPM75A4H	75A, High Accuracy Split-Core CT, 30' lead	0.2%
METSEHDPM150A12H	150A, High Accuracy Split-Core CT, 12' lead	0.2%
METSEHDPM150A30H	150A, High Accuracy Split-Core CT, 30' lead	0.2%
SUN4		
METSEHDPM300A12H	300A, High Accuracy Split-Core CT, 12' lead	0.2%
METSEHDPM300A30H	300A, High Accuracy Split-Core CT, 30' lead	0.2%
METSEHDPM400A12H	400A, High Accuracy Split-Core CT, 12' lead	0.2%
METSEHDPM400A30H	400A, High Accuracy Split-Core CT, 30' lead	0.2%
SUS4		
METSEHDPM150A12	150A, Split-Core CT, 12' lead	0.5%
METSEHDPM150A30	150A, Split-Core CT, 30' lead	0.5%
METSEHDPM150A60	150A, Split-Core CT, 60' lead	0.5%
METSEHDPM150A5	150A, Split-Core CT, HDPM6000S, 5" lead with connector	0.5%
METSEHDPM150A16	150A, Split-Core CT, HDPM6000B, 16" lead	0.5%
METSEHDPM300A12	300A, Split-Core CT, 12' lead	0.5%
METSEHDPM300A30	300A, Split-Core CT, 30' lead	0.5%
METSEHDPM300A60	300A, Split-Core CT, 60' lead	0.5%
METSEHDPM300A5	300A, Split-Core CT, HDPM6000S, 5" lead with connector	0.5%
METSEHDPM300A16	300A, Split-Core CT, HDPM6000B 16" lead	0.5%
METSEHDPM400A12	400A, Split-Core CT, 12' lead	0.5%
METSEHDPM400A30	400A, Split-Core CT, 30' lead	0.5%
METSEHDPM400A60	400A, Split-Core CT, 60' lead	0.5%
METSEHDPM400A5	400A, Split-Core CT, HDPM6000S, 5" lead with connector	0.5%
METSEHDPM400A16	400A, Split-Core CT, HDPM6000B 16" lead	0.5%
METSEHDPM600A12	600A, Split-Core CT, 12' lead	0.5%
METSEHDPM600A30	600A, Split-Core CT, 30' lead	0.5%
METSEHDPM600A60	600A, Split-Core CT, 60' lead	0.5%
METSEHDPM600A5H	600A, Split-Core CT, HDPM6000S, 5" lead with connector	0.5%
METSEHDPM600A16H	600A, Split-Core CT, HDPM6000B 16" lead	0.5%
SUSF		
METSEHD150A12	150A, Split-Core CT, 1"x1", 12' lead	1%
METSEHD150A30	150A, Split-Core CT, 1"x1", 30' lead	1%
METSEHD150A60	150A, Split-Core CT, 1"x1", 60' lead	1%
METSEHD300A12	300A, Split-Core CT, 1"x1", 12' lead	1%
METSEHD300A30	300A, Split-Core CT, 1"x1", 30' lead	1%