

Product datasheet

Specifications



LINERGY BW 4P INSULATED B.BAR 400A L1400

04128

⚠ Discontinued on: 23 Sept 2025

⚠ Discontinued

Main

Range	Linergy
Range of product	Linergy
Product or component type	Busbar
Product name	Linergy BW
Range compatibility	Prisma Prisma G enclosure Prisma Prisma P enclosure
IP degree of protection	IPxx B
Busbar description	Insulated bar
Quantity per set	Set of 1

Complementary

Poles description	4P
Installation direction	Vertical, operating position: rear
installation description	Cubicle - width 650 mm Floor-standing enclosure - width 600 mm Wall-mounted enclosure - width 600 mm
[U] rated insulation voltage	750 V
[Uimp] rated impulse withstand voltage	8 kV
[Ie] rated operational current	400 A
[Icw] rated short-time withstand current	20 kA (1 s)
[Ipk] rated peak withstand current	52.5 kA
I ² t on activation	400000 kA ² .s
Permissible current	400 A
Length	1400 mm
Net weight	8.94 kg
Type of busbar connection	M6 threaded hole
Connection pitch	Connection each 25 mm

Environment

Standards	IEC 61439-1 IEC 61439-2
Product certifications	ASEFA

Mechanical robustness Seismic tests structure reinforcement - 2.5G conforming to IEC 60068-2-57

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	4.5 cm
Package 1 Width	13 cm
Package 1 Length	152.5 cm
Package 1 Weight	8.97 kg

Contractual warranty

Warranty (in months) 18



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Packaging

Halogen-free status	Halogen free plastic parts product
PVC free	Yes
Silicone-free	Yes

Use Longer

Lifetime extension

Repair	No
--------	----

Use Again

Repack and remanufacture

Take-back	No
WEEE Label	The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins