

Product datasheet

Specifications



passive filter, Altivar, 217A, 460V,
60Hz, for variable speed drive

VW3A4656

⚠ End-of-service on: 24 Nov 2021

⚠ Discontinued

Main

Product or component type	Passive filter
Product specific application	Reduction of current harmonics

Complementary

Range compatibility	Altivar 71 Altivar 61
[Us] rated supply voltage	480 V +/- 10 %
power supply frequency	60 Hz +/- 5 %
Quantity per drive	1 filter per drive for ATV61HC13N4 1 filter per drive for ATV71HC13N4 2 filters per drive for ATV61HC25N4 2 filters per drive for ATV71HC25N4
[In] rated current	217 A
Network number of phases	3 phases
THDI	10 % for ATV61HC13N4 ATV61H motor: 132 kW/200 hp 10 % for ATV61HC25N4 ATV61H motor: 250 kW/400 hp 10 % for ATV71HC13N4 ATV71H motor: 132 kW/200 hp 10 % for ATV71HC25N4 ATV71H motor: 250 kW/400 hp
Max current	1.5 x nominal current
Efficiency	98 %
Cos phi	1 (150 % of line current) 0.85 (75 % of line current) 0.99 (100 % of line current)
Electrical connection	bare wires diameter: 16.5 mm
Electrical insulation class	Class F
Net weight	119 kg

Environment

IP degree of protection	IP20
Relative humidity	5...85 % without condensation
Ambient air temperature for operation	40...55 °C (with current derating 3 % per °C) 5...40 °C (without current derating)
Ambient air temperature for storage	-25...55 °C
Operating altitude	<= 1000 m without current derating > 1000...4000 m with current derating 5 % per 1000 m

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer

Lifetime extension	
Repair	No