


Product datasheet

Specifications



AC servo motors BRH - 1.86 N.m - 1500 rpm - untapped shaft - without brake- IP41

BRH0574P00A2A

Main

Product or component type	Motion servo motors
Component name	BRH
Continuous stall torque	1.3 N.m
Peak stall torque	4.73 N.m for LXM05AD17F1 4.73 N.m for LXM05AD17M2 4.73 N.m for LXM05AD17M3X 4.73 N.m for LXM05BD17F1 4.73 N.m for LXM05BD17M2 4.73 N.m for LXM05BD17M3X 4.73 N.m for LXM05CD17F1 4.73 N.m for LXM05CD17M2 4.73 N.m for LXM05CD17M3X 4.9 N.m for LXM05AD22N4 4.9 N.m for LXM05BD22N4 4.9 N.m for LXM05CD22N4
Nominal output power	190 W for LXM05AD17F1 190 W for LXM05BD17F1 190 W for LXM05CD17F1 510 W for LXM05AD17M2 510 W for LXM05AD17M3X 510 W for LXM05BD17M2 510 W for LXM05BD17M3X 510 W for LXM05CD17M2 510 W for LXM05CD17M3X 630 W for LXM05AD22N4 630 W for LXM05BD22N4 630 W for LXM05CD22N4
Nominal speed	1500 rpm for LXM05AD17F1 1500 rpm for LXM05BD17F1 1500 rpm for LXM05CD17F1 4500 rpm for LXM05AD17M2 4500 rpm for LXM05AD17M3X 4500 rpm for LXM05BD17M2 4500 rpm for LXM05BD17M3X 4500 rpm for LXM05CD17M2 4500 rpm for LXM05CD17M3X 6000 rpm for LXM05AD22N4 6000 rpm for LXM05BD22N4 6000 rpm for LXM05CD22N4
Maximum mechanical speed	8000 rpm
Product compatibility	LXM05AD17F1 at 115 V single phase LXM05AD17M2 at 230 V single phase LXM05AD17M3X at 230 V 3 phases LXM05AD22N4 at 400/480 V 3 phases LXM05BD17F1 at 115 V single phase LXM05BD17M2 at 230 V single phase LXM05BD17M3X at 230 V 3 phases LXM05BD22N4 at 400/480 V 3 phases LXM05CD17F1 at 115 V single phase LXM05CD17M2 at 230 V single phase LXM05CD17M3X at 230 V 3 phases LXM05CD22N4 at 400/480 V 3 phases
Shaft end	Untapped

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

IP degree of protection	IP41
Encoder type	Single turn SinCos Hiperface
Speed feedback resolution	16384 points/turn
Holding brake	Without
Mounting support	International standard flange
Electrical connection	Rotatable right-angled connectors
Nominal torque	1 N.m for LXM05AD22N4 1 N.m for LXM05BD22N4 1 N.m for LXM05CD22N4 1.08 N.m for LXM05AD17M2 1.08 N.m for LXM05AD17M3X 1.08 N.m for LXM05BD17M2 1.08 N.m for LXM05BD17M3X 1.08 N.m for LXM05CD17M2 1.08 N.m for LXM05CD17M3X 1.22 N.m for LXM05AD17F1 1.22 N.m for LXM05BD17F1 1.22 N.m for LXM05CD17F1
Number of poles	10
Maximum radial force Fr	100 N at 6000 rpm 101 N at 5000 rpm 103 N at 4000 rpm 106 N at 3000 rpm 112 N at 2000 rpm 152 N at 1000 rpm

Complementary

Range compatibility	Lexium 05
Switching frequency	8 kHz
Maximum current Irms	11 A for LXM05AD17F1 11 A for LXM05AD17M2 11 A for LXM05AD17M3X 11 A for LXM05BD17F1 11 A for LXM05BD17M2 11 A for LXM05BD17M3X 11 A for LXM05CD17F1 11 A for LXM05CD17M2 11 A for LXM05CD17M3X 11.35 A for LXM05AD22N4 11.35 A for LXM05BD22N4 11.35 A for LXM05CD22N4
Torque constant	0.46 N.m/A at 120 °C
Back emf constant	29.3 V/krpm at 120 °C
Rotor inertia	0.42 kg.cm² with brake 0.42 kg.cm² without brake
Stator resistance	4.3 Ohm
Stator inductance	9 mH
Maximum axial force Fa	0.2 x Fr
Net weight	2 kg



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer

Lifetime extension	
Repair	No