

# Product data sheet

Specifications



## TeSys Integral - coil - 36 V AC 60 Hz

LX1LD030

⚠ Discontinued on: Dec 23, 2020

⚠ Discontinued

### Main

Range	TeSys
Product or Component Type	Coil
Range compatibility	TeSys TeSys Integral contactor breaker
Device short name	LX1
Control circuit type	AC 60 Hz
[Uc] control circuit voltage	36 V AC 60 Hz
Average resistance	0.503 Ohm 68 °F (20 °C)
Inductance of closed circuit	0.106 H

### Complementary

Control circuit voltage limits	Operational: 0.85...1.1 Uc (at <131 °F (55 °C)) Drop-out: 0.25...0.7 Uc (at <131 °F (55 °C))
Inrush power in VA	420...500 VA 60 Hz cos phi 0.55
Hold-in power consumption in VA	24...36 VA 60 Hz cos phi 0.28

### Environment

Net Weight	0.7 lb(US) (0.3 kg)
------------	---------------------

### Ordering and shipping details

Category	18402-WORLD SERVICE PARTS(CONTROL ACCESS)
Discount Schedule	CP10
GTIN	3389110246438
Returnability	No

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better



#### Materials and Substances

[EU RoHS Directive](#)

Pro-active compliance (Product out of EU RoHS legal scope)

### Use Longer



#### Lifetime extension

Repair

No