


# Product datasheet

Specifications



## TeSys Deca - contactor coil - LX1D6 - 20 V AC 50/60 Hz for 40 to 95 A contactor

LX1D6Z7

⚠ Discontinued on: 10 Oct 2020

⚠ Discontinued

### Main

|                              |                  |
|------------------------------|------------------|
| Range                        | TeSys            |
| Product or component type    | Contactor coil   |
| Device short name            | LX1D6            |
| Control circuit type         | AC at 50/60 Hz   |
| [Uc] control circuit voltage | 20 V AC 50/60 Hz |
| Product compatibility        | LC1D40...D95     |

### Complementary

|                                 |  |
|---------------------------------|--|
| Coil technology                 | Without built-in suppressor module   |
| Control circuit voltage limits  | Operational: 0.85...1.1 U <sub>c</sub> at 50/60 Hz (at <55 °C)               |
| Inrush power in VA              | 245 VA 60 Hz cos phi 0.75 (at 20 °C)<br>245 VA 50 Hz cos phi 0.75 (at 20 °C) |
| Hold-in power consumption in VA | 26 VA 60 Hz cos phi 0.3 (at 20 °C)<br>26 VA 50 Hz cos phi 0.3 (at 20 °C)     |

### Environment

|            |         |
|------------|---------|
| Net weight | 0.28 kg |
|------------|---------|

### Packing Units

|                              |     |
|------------------------------|-----|
| Unit Type of Package 1       | PCE |
| Number of Units in Package 1 | 1   |

### Contractual warranty

|                      |    |
|----------------------|----|
| Warranty (in months) | 18 |
|----------------------|----|

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Longer



#### Lifetime extension

Repair

No