

Product data sheet

Specifications



Power cable SH3 motor to Lexium 52/62 drive, 1,5mm2, y-tec, 10m

VW3E1166R100

Product availability: Non-Stock - Not normally stocked in distribution facility

Main

Range of Product	PacDrive 3
Product or Component Type	Power cable

Complementary

Range Compatibility	Lexium 62 Lexium 52
Product compatibility	LXM 62 servo drive LXM 52 servo drive SH3040 servo motor
Type of Cable	Shielded cable
Connector type	Y-TEC quicklock, round shape
Material	Metal
Cable cross section	4 x 0.002 in² (1.0 mm²)
Cable length	32.8 ft (10 m)
Net Weight	5.05 lb(US) (2.29 kg)
Accessory / separate part category	Connection accessories

Ordering and shipping details

Category	US1PC5218359
Discount Schedule	PC52
GTIN	3606489780937
Returnability	No
Country of origin	PL

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	2.205 in (5.600 cm)
Package 1 Width	14.488 in (36.800 cm)
Package 1 Length	14.882 in (37.800 cm)
Package weight(Lbs)	4.691 lb(US) (2.128 kg)

Contractual warranty

Warranty (in months)	18
----------------------	----

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	Not applicable, out of EU RoHS legal scope
REACH Regulation	REACH Declaration

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
Take-back	No