

Product datasheet

Specifications



TeSys F - specific contactor coil - 127 V DC low consumption

LX9FJ926

⚠ Discontinued on: 1 Nov 2020

⚠ Discontinued

Main

Range	TeSys
Product or component type	Specific contactor coil
Device short name	LX9FJ
Range compatibility	TeSys TeSys F LC1F contactor TeSys TeSys F DR2S resistor
Product compatibility	DR2SC LC1F400
Control circuit type	AC at 40...400 Hz low consumption DC low consumption
[Uc] control circuit voltage	110 V DC 110 V AC
Inductance of closed circuit	1.7 H
Average resistance	32.3 Ohm inrush at 20 °C 302 Ohm holding at 20 °C
Operating time	60 ms opening 20 ms closing
Mechanical durability	10 Mcycles
Maximum operating rate	3600 cyc/h 70 °C

Complementary

Coil technology	Without built-in suppressor module
Control circuit voltage limits	Operational: 0.85...1.1 Uc (at 55 °C) Drop-out: 0.3...0.5 Uc (at 55 °C)
Inrush power in W	430 W (at 20 °C)
Hold-in power consumption in W	22 W at 20 °C
Heat dissipation	11.4...13.9 W

Environment

Ambient air temperature for operation	-5...55 °C
Net weight	0.97 kg

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained](#) >

[How we assess product sustainability](#) >



Environmental footprint

Environmental Disclosure

[Product Environmental Profile](#)

Use Longer



Lifetime extension

Repair

No

Use Again



Repack and remanufacture

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins