


Product datasheet

Specifications



LINERGY BS MULTISTAGE B.BAR SUPPORT 630A

04192

⚠ Discontinued on: Sep 23, 2025

⚠ Discontinued

Main

Range	Linergy
Range of product	Linergy
Product or component type	Busbar support
Product name	Linergy BS
Range compatibility	Linergy Linergy BS busbar Prisma Prisma G enclosure

Complementary

Cubicle-device connection	Linergy BS lateral busbar
installation description	Floor-standing duct - width 300 mm Wall-mounted duct - width 300 mm
Permissible current	160 A - busbar cross section: 15 x 5 mm 250 A - busbar cross section: 20 x 5 mm 400 A - busbar cross section: 32 x 5 mm 630 A - busbar cross section: 32 x 8 mm
[Icw] rated short-time withstand current	10 kA (1 s) at 160 A for 450 mm between support centres 20 kA (1 s) at 400 A for 300 mm between support centres 13 kA (1 s) at 250 A for 450 mm between support centres 15 kA (1 s) at 400 A for 450 mm between support centres 15 kA (1 s) at 630 A for 450 mm between support centres 20 kA (1 s) at 630 A for 300 mm between support centres 25 kA (0.6 s) at 400 A for 300 mm between support centres 25 kA (1 s) at 630 A for 300 mm between support centres
Product weight	0.2 kg
Quantity per set	Set of 1

Environment

Standards	IEC 61439-1 IEC 61439-2
Product certifications	ASEFA

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	2 cm
Package 1 Width	11.5 cm
Package 1 Length	23.5 cm
Package 1 Weight	200 g

Contractual warranty

Warranty (in months)

18



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better



Materials and Substances

EU RoHS Directive

[Compliant](#)

Halogen-free status

Halogen free plastic parts product

PVC free

Yes

Silicone-free

Yes

Use Longer



Lifetime extension

Repair

No

Use Again



Repack and remanufacture

Take-back

No