

Product data sheet

Specifications



TeSys Integral - undervoltage trip - 24 V AC 50/60 Hz - without time delay

LA1LC072B

⚠ Discontinued on: Oct 8, 2021

⚠ Discontinued

Main

Range	TeSys
Device short name	LA1LC
Product or Component Type	Undervoltage trip
Product Compatibility	LD5 LD4
Range compatibility	TeSys TeSys Integral contactor breaker

Complementary

[Uc] control circuit voltage	24 V AC 50/60 Hz
Time delay	Without time delay
Voltage release type	Instantaneous Undervoltage release
Control circuit voltage limits	0.8...1.1 Uc
Threshold tripping voltage	0.35...0.7 Uc
Inrush power in VA	8 VA AC
Hold-in Power Consumption in VA	4 VA AC
Quantity per Set	Set of 10
Net Weight	0.33 lb(US) (0.15 kg)

Ordering and shipping details

Category	18402-WORLD SERVICE PARTS(CONTROL ACCESS)
Discount Schedule	CP10
GTIN	3389110182057
Returnability	No
Country of origin	CZ

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	1.7 in (4.4 cm)
Package 1 Width	2.5 in (6.3 cm)
Package 1 Length	4.5 in (11.5 cm)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Package weight(Lbs)

4.7 oz (134 g)



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better



Materials and Substances

[EU RoHS Directive](#)

Compliant

Use Longer



Lifetime extension

Repair

No

Use Again



Repack and remanufacture

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.