

# Product data sheet

Specifications



IEC Starter, TeSys LE1, full voltage, non reversing, 32A rated, with 60A fusible disconnect, 25HP at 575VAC, 120VAC 50/60 Hz coil, NEMA 1

LE1D328C62OG70

## Main

Product or component type	Full voltage starter
Range of product	Instakits
Starter Type	Non reversing
Disconnect Type	fusible disconnect

## Complementary

Control Circuit Voltage	120 V AC 50/60 Hz
Current Rating	32 A
Horsepower Rating	2 hp 120 V AC, 1 phase 5 hp 240 V AC, 1 phase 10 hp 208 V AC, 3 phases 10 hp 230 V AC, 3 phases 20 hp 460 V AC, 3 phases 25 hp 575 V AC, 3 phases
Maximum Voltage Rating	600 V AC
Auxiliary Contacts	1 NO + 1 NC
Protection type	Switch-disconnector fuse 60 A
Location of connection	Line

## Environment

Product certifications	CSA IEC UL
Enclosure Type	NEMA 1 steel

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	11.00 in (27.94 cm)
Package 1 Width	13.00 in (33.02 cm)
Package 1 Length	28.50 in (72.39 cm)
Package 1 Weight	37.761 lb(US) (17.128 kg)

## Contractual warranty

Warranty (in months)	18
----------------------	----



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better



#### Materials and Substances

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
EU RoHS Directive	<a href="#">Compliant</a>
REACH Regulation	<a href="#">Free of Substances of Very High Concern above the threshold</a>
PVC free	Yes

### Use Longer




#### Lifetime extension

Repair	No
--------	----

### Use Again



#### Repack and remanufacture

Circularity Profile	No need of specific recycling operations
Take-back	No
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins