

# Product datasheet

Specifications



## Auxiliary contacts, TeSys GS, 2 C/O, early break, side mounting, for GS1 32A with direct front/right handle

GS1AM211

⚠ Discontinued on: 20 Jun 2023

⚠ To be discontinued

### Main

Range of product	TeSys
Device short name	GS1AM
Product or component type	Auxiliary contact
Contact application	O and I position signalling
Range compatibility	TeSys TeSys GS GS1D fuse-switch disconnecter
Contacts type and composition	2 C/O
Contact operation	Early-break
[I <sub>th</sub> ] conventional free air thermal current	16 A (at 40 °C)
[I <sub>e</sub> ] rated operational current	5 A at 127 V AC-15 4 A at 230 V AC-15 3 A at 400/415 V AC-15 2 A at 440 V AC-15 12 A at 24 V DC-13 2 A at 48 V DC-13 0.6 A at 110 V DC-13 0.4 A at 220 V DC-13

### Complementary

Mechanical durability	1 Mcycles
Electrical durability	30000 cycles AC-15
switch rated current	32 A
Fuse type	NFC DIN BS
Type of operating handle	Direct frontal
Mounting location	Right side
Net weight	0.07 kg

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	3.0 cm
Package 1 Width	8.0 cm
Package 1 Length	12.0 cm
Package 1 Weight	83.0 g

Excluding VAT, FCA Jabal Ali & amp; are subject to change – check with your local distributor.

<b>Unit Type of Package 2</b>	S01
<b>Number of Units in Package 2</b>	7
<b>Package 2 Height</b>	15.0 cm
<b>Package 2 Width</b>	15.0 cm
<b>Package 2 Length</b>	40.0 cm
<b>Package 2 Weight</b>	806.0 g

## **Contractual warranty**

<b>Warranty (in months)</b>	18
-----------------------------	----



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better



#### Materials and Substances

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No
EU RoHS Directive	<a href="#">Compliant</a>
REACH Regulation	<a href="#">Free of Substances of Very High Concern above the threshold</a>

### Use Longer




#### Lifetime extension

Repair	No
--------	----

### Use Again



#### Repack and remanufacture

Take-back	Nej
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins