

# Product data sheet

Specifications



## TeSys integral - auxiliary contact - 4 NO + 1 NC

LA1LC0129

⚠ Discontinued on: Jul 12, 2021

⚠ Discontinued

### Main

Range	TeSys
Device short name	LA1LC
Product or Component Type	Auxiliary contact
Device Application	Control

### Complementary

Range compatibility	TeSys TeSys Integral contactor breaker
Mounting Location	Right side
Auxiliary contacts operation	Instantaneous
Pole contact composition	2 NO + 1 NC contactor state 1 NO tripped 1 NO tripped on short-circuit
[Ui] rated insulation voltage	690 V
[Ith] conventional free air thermal current	6 A
Connections - terminals	screw clamp terminals 2 0.002 in <sup>2</sup> (1.5 mm <sup>2</sup> ) screw clamp terminals 1 0.004 in <sup>2</sup> (2.5 mm <sup>2</sup> )
Net Weight	0.49 lb(US) (0.22 kg)

### Environment

Environmental characteristic	Standard environment
------------------------------	----------------------

### Ordering and shipping details

Category	22384-STARTERS,INTEGRAL,ACCESS
Discount Schedule	I11
GTIN	3389118091610
Returnability	No
Country of origin	CZ

### Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	1.2 in (3 cm)
Package 1 Width	7.09 in (18 cm)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

---

**Package 1 Length** 4.9 in (12.5 cm)

---

**Package weight(Lbs)** 10.7 oz (302 g)

---



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

#### Materials and Substances

[EU RoHS Directive](#)

Compliant

California proposition 65

WARNING: This product can expose you to chemicals including: Styrene, which is known to the State of California to cause cancer. For more information go to [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov)

### Use Longer

#### Lifetime extension

Repair

No

### Use Again

#### Repack and remanufacture

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.