

# Product data sheet

Specifications



## undervoltage release UVR - 100..110 V AC, 100..110 V DC - for EZC400

EZ4UVR110ACDC

⚠ Discontinued on: Nov 1, 2020

⚠ Discontinued

### Main

Range	EasyPact
Range of product	EZC400
Device short name	UVR
Product or component type	Voltage release
Device application	Control
Voltage release type	Undervoltage release
[Uc] control circuit voltage	100...110 V AC 50/60 Hz 100...110 V DC
Circuit breaker mounting mode	Internal mounting
Range compatibility	EasyPact EasyPact EZC

### Complementary

Operating threshold	0.35...0.7 x Un opening 0.85 x Un closing
Supply inrush power	5 VA 10 W
Auxiliary connection terminal	Pre-wired 0...1.5 mm <sup>2</sup>

### Contractual warranty

Warranty (in months)	18
----------------------	----

List Price displayed is VAT EXCLUSIVE.



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Longer



#### Lifetime extension

Repair

No

### Use Again



#### Repack and remanufacture

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins