

# Product data sheet

Specifications



## TeSys Integral - shunt trip - 24 V AC 50/60 Hz - without time delay

LA1LC071B

⚠ Discontinued on: Jul 12, 2021

⚠ Discontinued

### Main

|                           |  |
|---------------------------|--|
| Range                     | TeSys                                  |
| Device short name         | LA1LC                                  |
| Product or Component Type | Shunt trip                             |
| Product Compatibility     | LD4<br>LD5                             |
| Device Application        | Control                                |
| Range compatibility       | TeSys TeSys Integral contactor breaker |

### Complementary

|                                 |                             |
|---------------------------------|-----------------------------|
| [Uc] control circuit voltage    | 24 V AC 50/60 Hz            |
| Time delay                      | Without time delay          |
| Voltage release type            | Shunt trip<br>Instantaneous |
| Control circuit voltage limits  | 0.7...1.1 Uc                |
| Threshold tripping voltage      | 0.35...0.7 Uc               |
| Inrush power in VA              | 8 VA AC                     |
| Hold-in Power Consumption in VA | 4 VA AC                     |
| Operating time                  | >= 10 ms                    |
| Connections - terminals         | screw connection            |
| Quantity per Set                | Set of 10                   |
| Net Weight                      | 0.33 lb(US) (0.15 kg)       |

### Ordering and shipping details

|                   |                                |
|-------------------|--------------------------------|
| Category          | 22384-STARTERS,INTEGRAL,ACCESS |
| Discount Schedule | I11                            |
| GTIN              | 3389110181951                  |
| Returnability     | No                             |
| Country of origin | CZ                             |

### Packing Units

|                        |     |
|------------------------|-----|
| Unit Type of Package 1 | PCE |
| Nbr. of units in pkg.  | 1   |

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

|                            |                  |
|----------------------------|------------------|
| <b>Package 1 Height</b>    | 1.6 in (4 cm)    |
| <b>Package 1 Width</b>     | 2.6 in (6.5 cm)  |
| <b>Package 1 Length</b>    | 4.5 in (11.5 cm) |
| <b>Package weight(Lbs)</b> | 4.7 oz (134 g)   |



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better



#### Materials and Substances

[EU RoHS Directive](#)

Compliant

California proposition 65

WARNING: This product can expose you to chemicals including: Styrene, which is known to the State of California to cause cancer. For more information go to [www.P65Warnings.ca.gov](http://www.P65Warnings.ca.gov)

### Use Longer



#### Lifetime extension

Repair

No

### Use Again



#### Repack and remanufacture

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.