

Product data sheet

Specifications



IEC Starter, TeSys LE1, full voltage, non reversing, unfused, 80A rated, 60HP at 575VAC, 120VAC 50/60 Hz coil, NEMA 1

LE1D803A60OG70

Main

Product or component type	Full voltage starter
Range of product	Instakits
Starter Type	Non reversing

Complementary

Control Circuit Voltage	120 V AC 50/60 Hz
Current Rating	125 A
Horsepower Rating	7.5 hp 120 V AC, 1 phase 15 hp 240 V AC, 1 phase 25 hp 208 V AC, 3 phases 30 hp 230 V AC, 3 phases 60 hp 460 V AC, 3 phases 60 hp 575 V AC, 3 phases
Maximum Voltage Rating	600 V AC
Auxiliary Contacts	1 NO + 1 NC
Protection type	Switch-disconnector fuse
Location of connection	Line

Environment

Product certifications	UL IEC CSA
Enclosure Type	NEMA 1 steel

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	11.00 in (27.94 cm)
Package 1 Width	13.50 in (34.29 cm)
Package 1 Length	19.00 in (48.26 cm)
Package 1 Weight	20.331 lb(US) (9.222 kg)

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better



Materials and Substances

Packaging made with recycled cardboard	Yes
Packaging without single use plastic	Yes
EU RoHS Directive	Compliant
REACH Regulation	Free of Substances of Very High Concern above the threshold
PVC free	Yes

Use Longer




Lifetime extension

Repair	No
--------	----

Use Again



Repack and remanufacture

Circularity Profile	No need of specific recycling operations
Take-back	No
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins