

Product datasheet

Specifications



MN undervoltage release, GoPact MCCB 125, 415VAC 50/60Hz

G12UVR415AC

Main

Range of product	GoPact MCCB
Product or component type	Voltage release
Device short name	MN
Device application	Control
Range compatibility	GoPact MCCB 125
Voltage release type	Undervoltage release
[Uc] control circuit voltage	415 V AC 50/60 Hz

Complementary

Threshold tripping voltage	0.35...0.7 Un opening 0.85...1.1 Un closing
Max supply holding power consumption	3.5 VA
Max supply pick-up power consumption	5 VA
Response time	25 ms

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	6.5 cm
Package 1 Width	8.5 cm
Package 1 Length	4.8 cm
Package 1 Weight	900 g
Unit Type of Package 2	S02
Number of Units in Package 2	20
Package 2 Height	15 cm
Package 2 Width	30 cm
Package 2 Length	40 cm
Package 2 Weight	2.115 kg
Unit Type of Package 3	P06
Number of Units in Package 3	320
Package 3 Height	60 cm
Package 3 Width	60 cm

Package 3 Length	80 cm
------------------	-------

Package 3 Weight	42.34 kg
------------------	----------

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)



Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

Use Better



Materials and Substances

Packaging made with recycled cardboard

Yes

Packaging without single use plastic

No

SCIP Number

1bd54731-3e91-4a6a-9f3a-c4c99a531acc

EU RoHS Directive

[Compliant By Exemption](#)

REACH Regulation

[Reference contains Substances of Very High Concern above the threshold](#)

Halogen-free status

Halogen free plastic parts product

PVC free

Yes

Silicone-free

Yes

Use Longer



Lifetime extension

Repair

No

Use Again



Repack and remanufacture

End of life manual availability

[End of Life Information](#)

Take-back

No

Technical Illustration

Dimensions

