

# Product datasheet

Specifications



## DOL combination starter , TeSys Deca, 0.4...0.63 A , 400V AC

GV2DM104V7

EAN Code: 3389110781892

! Discontinued

### Main

|                           |  |
|---------------------------|--|
| Range of product          | TeSys Deca   |
| Device short name         | GV2DM  |
| Product or component type | Motor starter  |
| Motor starter type        | Non reversing  |
| Coordination type         | Type 1   |
| Poles description         | 3P   |
| Utilisation category      | AC-3   |
| Motor power kW            | 0.12 kW at 400/415 V AC 50/60 Hz<br>0.18 kW at 400/415 V AC 50/60 Hz<br>0.18 kW at 440 V AC 50/60 Hz |
| Magnetic tripping current | 8 A  |

### Complementary

|                                     |   |
|-------------------------------------|---|
| Device composition                  | 1 3-pole contactor<br>1 motor circuit breaker type GV2ME<br>1 combination block GV2AF3  |
| Thermal protection adjustment range | 0.4...0.63 A  |
| Rated breaking capacity             | Iq 50 kA at 400/415 V conforming to IEC 60947-4-1<br>Iq 50 kA at 440 V conforming to IEC 60947-4-1<br>Iq 50 kA at 500 V conforming to IEC 60947-4-1 |
| Net weight                          | 0.596 kg  |
| Height                              | 176.4 mm  |
| Width                               | 45 mm   |
| Depth                               | 99.6 mm   |

### Packing Units

|                              |     |
|------------------------------|-----|
| Unit Type of Package 1       | PCE |
| Number of Units in Package 1 | 1   |

### Contractual warranty

|                      |    |
|----------------------|----|
| Warranty (in months) | 18 |
|----------------------|----|



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Longer



#### Lifetime extension

Repair

No

### Use Again



#### Repack and remanufacture

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins