

Product data sheet

Specifications



Circuit breaker, MasterPacT MTZ2, UL 489, max 3000A rated, 3 pole, drawout mount, H breaking cap, 600VAC, w/o Micrologic trip unit, w/ ArcBlok

LV839144

Main

Product name	MasterPact MTZ2
Device short name	MTZ2 30 H
Product or Component Type	Circuit breaker
Device Application	Protection
Poles description	3P
Network type	AC
Network Frequency	50/60 Hz
Breaking capacity code	H

Complementary

Control Type	Push-button
Mounting Mode	Drawout
Mounting Support	Base plate Rails
Line Rated Current	3000 A 104 °F (40 °C)
Circuit breaker CT rating	3000 A
performance level	100 kA Icu 240 V AC 50/60 Hz UL 489 100 kA Icu 480 V AC 50/60 Hz UL 489 85 kA Icu 600 V AC 50/60 Hz UL 489
Mechanical durability	12500 cycles ANSI C37.50
Electrical durability	2800 cycles ANSI C37.50
Connection pitch	4.5 in (115 mm)
[Icw] rated short-time withstand current	65 kA 0.5 s UL 489
Integral instant protection	135...165 kA
Rated breaking and making capacity	90 kA
Maximum breaking time	25...30 ms
Maximum closing response time	70 ms
Height	17.3 in (438.8 mm)
Width	17.5 in (444.3 mm)
Depth	16.8 in (426.8 mm)

Packing Units

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better

Materials and Substances	
Packaging made with recycled cardboard	Yes
Packaging without single use plastic	No

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
Take-back	No