

Product datasheet

Specifications



Reversing motor starter combination, TeSys Deca, 9-14 A, coil 24 V DC low

GV2DP216BL

EAN Code: 3389110060225

! Discontinued

Main

Range of product	TeSys
Device short name	GV2DP
Product or component type	Motor starter
Motor starter type	Reversing
Coordination type	Type 2
Poles description	3P
Utilisation category	AC-3
Motor power kW	5.5 kW at 400/415 V AC 50/60 Hz 5.5 kW at 440 V AC 50/60 Hz 7.5 kW at 440 V AC 50/60 Hz 9 kW at 500 V AC 50/60 Hz 7.5 kW at 500 V AC 50/60 Hz
[Uc] control circuit voltage	24 V DC
Magnetic tripping current	170 A

Complementary

Device composition	1 3-pole reversing contactor 1 combination block GV2AF3 1 motor circuit breaker type GV2P
Thermal protection adjustment range	9...14 A
Rated breaking capacity	I _q 130 kA at 400/415 V conforming to IEC 60947-4-1 I _q 50 kA at 440 V conforming to IEC 60947-4-1 I _q 42 kA at 500 V conforming to IEC 60947-4-1
Net weight	1.163 kg
Height	186.8 mm
Width	90 mm
Depth	111.9 mm

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer



Lifetime extension

Repair

No