

Product datasheet

Specifications



DOL combination starter , TeSys Deca, 13...18 A , 240 V AC

GV2DM120U7

EAN Code: 3389110782035

! Discontinued

Main

Range of product	TeSys Deca
Device short name	GV2DM
Product or component type	Motor starter
Motor starter type	Non reversing
Coordination type	Type 1
Poles description	3P
Utilisation category	AC-3
Motor power kW	7.5 kW at 400/415 V AC 50/60 Hz 9 kW at 440 V AC 50/60 Hz 7.5 kW at 440 V AC 50/60 Hz 9 kW at 500 V AC 50/60 Hz
Magnetic tripping current	223 A

Complementary

Device composition	1 combination block GV2AF3 1 3-pole contactor 1 motor circuit breaker type GV2ME
Thermal protection adjustment range	13...18 A
Rated breaking capacity	Iq 15 kA at 400/415 V conforming to IEC 60947-4-1 Iq 8 kA at 440 V conforming to IEC 60947-4-1 Iq 6 kA at 500 V conforming to IEC 60947-4-1
Net weight	0.606 kg
Height	176.4 mm
Width	45 mm
Depth	99.6 mm

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer



Lifetime extension

Repair

No

Use Again



Repack and remanufacture

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins