

# Product data sheet

Specifications



## FULL-VOLTAGE NON-REVERSING IEC STARTER UNFUSED TYPE 1

LE1D093A62OM70

⚠ Discontinued on: Jun 12, 2024

⚠ Discontinued

### Main

Product or component type	Full voltage starter
Range of product	Instakits
Starter Type	Non reversing

### Complementary

Control Circuit Voltage	600 V AC 50/60 Hz
Current Rating	9 A
Horsepower Rating	0.3 hp 120 V AC, 1 phase 1 hp 240 V AC, 1 phase 2 hp 208 V AC, 3 phases 2 hp 230 V AC, 3 phases 5 hp 460 V AC, 3 phases 7.5 hp 575 V AC, 3 phases
Maximum Voltage Rating	240 V AC 600 V AC
Auxiliary Contacts	1 NO + 1 NC
Location of connection	Line

### Environment

Product certifications	IEC UL CSA
Enclosure Type	NEMA 1 steel

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	11.00 in (27.94 cm)
Package 1 Width	9.50 in (24.13 cm)
Package 1 Length	15.0 in (38.1 cm)
Package 1 Weight	10.300 lb(US) (4.672 kg)

### Contractual warranty

Warranty (in months)	18
----------------------	----



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better



#### Materials and Substances

Packaging made with recycled cardboard	No
Packaging without single use plastic	No
EU RoHS Directive	<a href="#">Compliant</a>
PVC free	Yes

### Use Longer



#### Lifetime extension

Repair	No
--------	----

### Use Again



#### Repack and remanufacture

WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins
------------	---