

Product data sheet

Specifications



coil LX1-LB -300V AC 50Hz, 347 V
AC 60Hz

LX1LB300

⚠ Discontinued

Main

Range	TeSys
Device short name	LX1
Product or Component Type	Coil
[Uc] control circuit voltage	300 V AC 50 Hz 347 V AC 60 Hz
Value of inductance	6.6 H
Average resistance	773 Ohm at 68 °F (20 °C) +/- 10 %

Complementary

Range compatibility	TeSys LX1 contactor
Power consumption in VA	75 VA AC 0.55 50 Hz inrush 8 VA AC 0.28 50 Hz sealed
Net Weight	0.143 lb(US) (0.065 kg)

Ordering and shipping details

Category	18402-WORLD SERVICE PARTS(CONTROL ACCESS)
Discount Schedule	CP10
GTIN	3389110461473
Returnability	No

Contractual warranty

Warranty (in months)	18
----------------------	----

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer



Lifetime extension

Repair

No