


Product data sheet

Specifications



2nd MX opening voltage release,
standard, Masterpact MTZ1
drawout, 12 VDC

LV847449

⚠ Discontinued on: Jan 23, 2021

⚠ Discontinued

Main

Range	MasterPact
Device short name	second MX
Product or Component Type	Voltage release
Device Application	Control
Range compatibility	Masterpact MasterPact MTZ1 circuit-breaker
Voltage release type	Shunt trip release

Complementary

Control Type	Standard
[Un] voltage power supply	12 V DC
Threshold tripping voltage	0.7...1.1 Un on opening
Holding power consumption	4.5 W
Circuit breaker mounting mode	Drawout
Maximum response time	60 ms on opening MasterPact MTZ1

Ordering and shipping details

GTIN	3606480813276
------	---------------

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	1.4 in (3.5 cm)
Package 1 Width	2.4 in (6 cm)
Package 1 Length	3.3 in (8.3 cm)
Package weight(Lbs)	2.568 lb(US) (1.165 kg)

Contractual warranty

Warranty (in months)	18
----------------------	----

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained](#) >

[How we assess product sustainability](#) >

Use Better

Materials and Substances	
EU RoHS Directive	Compliant
California proposition 65	WARNING: This product can expose you to chemicals including: DINP, which is known to the State of California to cause cancer, and DIDP, which is known to the State of California to cause birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.