


Product datasheet

Specifications



contactor coil, TeSys D LX1D, 208 V 60 Hz

LX1D8L6

EAN Code: 3389110898323

! Discontinued

Main

Range	TeSys
Product or component type	Contactor coil
Range compatibility	TeSys TeSys D LC1D contactor
Control circuit type	AC
Coil type	AC 60 Hz
[Uc] control circuit voltage	208 V AC 60 Hz

Complementary

Control circuit voltage limits	0.85...1.1 Uc (at <55 °C)
Average resistance	67.92 Ohm at 20 °C
Inrush power in VA	300 VA cos phi 0.8 3P or 4P (at 20 °C)
Hold-in power consumption in VA	22 VA 60 Hz cos phi 0.3 3P or 4P (at 20 °C)
Mechanical durability	10000000 cycles
Connections - terminals	Control circuit: connector 1 cable(s) 1...4 mm²flexible with cable end Control circuit: connector 1 cable(s) 1...4 mm²flexible without cable end Control circuit: connector 1 cable(s) 1...4 mm²solid without cable end Control circuit: connector 2 cable(s) 1...2.5 mm²flexible with cable end Control circuit: connector 2 cable(s) 1...4 mm²flexible without cable end
Tightening torque	Control circuit: 1.2 N.m - on connector
Net weight	0.26 kg

Environment

Ambient air temperature for operation	20 °C
---------------------------------------	-------

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Weight	285 g

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer

Lifetime extension	
Repair	No

Use Again

Repack and remanufacture	
WEEE Label	 The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins