

# Product datasheet

Specifications



## MX shunt trip, GoPact MCCB 200/250, 240VAC 50/60Hz

G20-25SHT240AC

**Price: 636.33 ZAR**

### Main

Range of product	GoPact MCCB
Product or component type	Voltage release
Device short name	MX
Device application	Control
Range compatibility	GoPact MCCB 200 GoPact MCCB 250
Voltage release type	Shunt trip
[Uc] control circuit voltage	240 V AC 50/60 Hz

### Complementary

Threshold tripping voltage	0.7...1.1 Un opening
Max supply pick-up power consumption	5 VA
Response time	25 ms

### Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	6.5 cm
Package 1 Width	8.5 cm
Package 1 Length	4.8 cm
Package 1 Weight	100 g
Unit Type of Package 2	S02
Number of Units in Package 2	20
Package 2 Height	15 cm
Package 2 Width	30 cm
Package 2 Length	40 cm
Package 2 Weight	2.315 kg
Unit Type of Package 3	P06
Number of Units in Package 3	320
Package 3 Height	60 cm
Package 3 Width	60 cm
Package 3 Length	80 cm

Excluding VAT and subject to change. Please check with your local distributor through "Where to buy"

---

Package 3 Weight	45.540 kg
------------------	-----------

## Contractual warranty

---

Warranty (in months)	18
----------------------	----



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)



### Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

## Use Better



### Materials and Substances

Packaging made with recycled cardboard

Yes

Packaging without single use plastic

No

[EU RoHS Directive](#)

Compliant with Exemptions

SCIP Number

Dbfa5a24-2300-4757-9388-243f4e4f2875

REACH Regulation

[REACH Declaration](#)

Halogen-free status

Halogen free plastic parts product

PVC free

Yes

Silicone-free

Yes

## Use Longer



### Lifetime extension

Repair

No

## Use Again



### Repack and remanufacture

End of life manual availability

[End of Life Information](#)

Take-back

No

Technical Illustration

Dimensions

---

