

# Product data sheet

Specifications



IEC Starter, TeSys LE1, full voltage, non reversing, unfused, 18A rated, 15HP at 575VAC, 120VAC 50/60 Hz coil, NEMA 1

LE1D183A60OG70

! Discontinued

! Discontinued on: Jun 12, 2024

## Main

Product or component type	Full voltage starter
Range of product	Instakits
Starter Type	Non reversing

## Complementary

Control Circuit Voltage	120 V AC 50/60 Hz
Current Rating	32 A
Horsepower Rating	25 hp 575 V AC, 3 phases 5 hp 208 V AC, 3 phases 5 hp 230 V AC, 3 phases 10 hp 460 V AC, 3 phases
Maximum Voltage Rating	600 V AC
Auxiliary Contacts	1 NO + 1 NC
Location of connection	Line

## Environment

Product certifications	CSA IEC UL
Enclosure Type	NEMA 1 steel

## Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	11.00 in (27.94 cm)
Package 1 Width	10.0 in (25.4 cm)
Package 1 Length	15.0 in (38.1 cm)
Package 1 Weight	10.249 lb(US) (4.649 kg)

## Contractual warranty

Warranty (in months)	18
----------------------	----



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better



#### Materials and Substances

Packaging made with recycled cardboard **Yes**

Packaging without single use plastic **Yes**

EU RoHS Directive [Compliant](#)

PVC free **Yes**

### Use Longer



#### Lifetime extension

Repair **No**

### Use Again



#### Repack and remanufacture

Take-back **Nej**

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins