

# Product data sheet

Specifications



main busbar kit, Altivar Process Modular, for 1 power module in cabinet

VW3A98ABMAAA

## Main

|                                       |                                                    |
|---------------------------------------|----------------------------------------------------|
| Range of product                      | Altivar Process Modular                            |
| Accessory / separate part category    | Cabling accessory                                  |
| Accessory / separate part type        | Busbar                                             |
| Product compatibility                 | Power module APM, 110...800 kW, 380...480 V        |
| Accessory / separate part destination | Single drive architecture                          |
| Device application                    | To connect 1 stand alone power module in a cabinet |

## Complementary

|                 |                     |
|-----------------|---------------------|
| Kit composition | 3 bar with holes    |
| Net weight      | 9.9 lb(US) (4.5 kg) |

## Packing Units

|                              |                           |
|------------------------------|---------------------------|
| Unit Type of Package 1       | PCE                       |
| Number of Units in Package 1 | 1                         |
| Package 1 Height             | 11.811 in (30.000 cm)     |
| Package 1 Width              | 15.748 in (40.000 cm)     |
| Package 1 Length             | 23.622 in (60.000 cm)     |
| Package 1 Weight             | 11.457 lb(US) (5.197 kg)  |
| Unit Type of Package 2       | S04                       |
| Number of Units in Package 2 | 2                         |
| Package 2 Height             | 11.811 in (30.000 cm)     |
| Package 2 Width              | 15.748 in (40.000 cm)     |
| Package 2 Length             | 23.622 in (60.000 cm)     |
| Package 2 Weight             | 25.353 lb(US) (11.500 kg) |

## Contractual warranty

|                      |    |
|----------------------|----|
| Warranty (in months) | 18 |
|----------------------|----|

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Use Better

| Materials and Substances               |                                                                             |
|----------------------------------------|-----------------------------------------------------------------------------|
| Packaging made with recycled cardboard | Yes                                                                         |
| Packaging without single use plastic   | No                                                                          |
| EU RoHS Directive                      | <a href="#">Compliant</a>                                                   |
| REACH Regulation                       | <a href="#">Free of Substances of Very High Concern above the threshold</a> |

### Use Longer

| Lifetime extension |    |
|--------------------|----|
| Repair             | No |

### Use Again

| Repack and remanufacture |    |
|--------------------------|----|
| Take-back                | No |