

Product datasheet

Specifications



MX shunt trip, GoPact MCCB 400/800, 240VAC 50/60Hz

G40-80SHT240AC

Main

Range of product	GoPact MCCB
Product or component type	Voltage release
Device short name	MX
Device application	Control
Range compatibility	GoPact MCCB 400 GoPact MCCB 800 EasyPact Solar MCCB 400 EasyPact Solar MCCB 800
Voltage release type	Shunt trip
[Uc] control circuit voltage	240 V AC 50/60 Hz

Complementary

Threshold tripping voltage	0.7...1.1 Un opening
Max supply pick-up power consumption	5 VA
Response time	25 ms

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	6.500 cm
Package 1 Width	8.500 cm
Package 1 Length	4.800 cm
Package 1 Weight	109.900 g
Unit Type of Package 2	S02
Number of Units in Package 2	20
Package 2 Height	15.000 cm
Package 2 Width	30.000 cm
Package 2 Length	40.000 cm
Package 2 Weight	2.515 kg

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)



Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

Use Better



Materials and Substances

Packaging made with recycled cardboard

Yes

Packaging without single use plastic

No

SCIP Number

Dbfa5a24-2300-4757-9388-243f4e4f2875

EU RoHS Directive

[Compliant By Exemption](#)

REACH Regulation

[Reference contains Substances of Very High Concern above the threshold](#)

Halogen-free status

Halogen free plastic parts product

PVC free

Yes

Silicone-free

Yes

Use Longer



Lifetime extension

Repair

No

Use Again



Repack and remanufacture

End of life manual availability

[End of Life Information](#)

Take-back

No

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

Technical Illustration

Dimensions

