

Product data sheet

Specifications

coil WB1-K - for CR1B.33



WB1KB135

⚠ Discontinued on: Dec 23, 2020

⚠ Discontinued

Important message: This product is no longer commercialized by Schneider Electric. As per 14 January 2022, the commercialization is managed by Lenoir Elec. Please follow the link <https://www.lenoir-elec.com/> for more details.

Main

Range	TeSys
Product or Component Type	Contacteur coil
Range compatibility	TeSys TeSys B CR1B.33 contactor
Control circuit type	AC
Coil type	Low consumption
[Uc] control circuit voltage	250 V DC

Complementary

Average resistance	61 Ohm 68 °F (20 °C)
Inrush power in VA	450...620 VA 1P
Inrush power in W	380...520 W 1P
Hold-in power consumption in VA	0.15...0.2 VA 50...400 Hz 1P
Hold-in power consumption in W	0.15...0.2 W 1P
Mechanical durability	1200000 cycles
Net Weight	2.47 lb(US) (1.12 kg)

Environment

Heat dissipation	7...10 W 50...400 Hz 1P
------------------	-------------------------

Ordering and shipping details

Category	18402-WORLD SERVICE PARTS(CONTROL ACCESS)
Discount Schedule	CP10
GTIN	3389110479560
Returnability	No

Packing Units

Unit Type of Package 1	PCE
Nbr. of units in pkg.	1
Package 1 Height	3.5 in (9 cm)
Package 1 Width	2.6 in (6.5 cm)
Package 1 Length	6.5 in (16.5 cm)

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

Package weight(Lbs)	2.575 lb(US) (1.168 kg)
---------------------	-------------------------

Contractual warranty

Warranty (in months)	18
----------------------	----



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Better



Materials and Substances

[EU RoHS Directive](#)

Pro-active compliance (Product out of EU RoHS legal scope)

Use Longer



Lifetime extension

Repair

No