

Product datasheet

Specifications

TeSys D - 4 DOL power & control splitter box 2x HE10



APP2R4H2

⚠ Discontinued on: 5 Mar 2020

⚠ Discontinued

Main

Range	TeSys
Product or component type	Power splitter box
Device application	Distribution
[In] rated current	50 A
Connector type	Input: 1 x HE10 (16 poles) Output: 1 x HE10 (8 poles)
Number of inputs	2 (per starter)
Number of outputs	1 per starter
Number of devices	4 starters per unit

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	8.5 cm
Package 1 Width	20.7 cm
Package 1 Length	7 cm
Package 1 Weight	474 g

Contractual warranty

Warranty (in months)	18
----------------------	----

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Use Longer



Lifetime extension

Repair

No

Use Again



Repack and remanufacture

WEEE Label



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins